

Thank you for using the CS+ integrated development environment.

This document describes the restrictions and points for caution. Read this document before using the product.

Contents

Chapter 1	Target Devices	2
Chapter 2	User's Manuals.....	3
Chapter 3	Keywords When Uninstalling the Product	4
Chapter 4	Changes.....	5
4.1.	Extensions to the checking of source code against MISRA-C:2012 rules [Professional edition]	5
4.2.	Writing the #pragma section directive within functions	5
4.3.	C99 standard library functions	6
4.4.	Allowing the specification of the same module names during the generation of a library	6
4.5.	Improvement to code generated for loop processing.....	7
4.6.	Rectified point for caution.....	10
4.7.	Other changes and improvements	10
Chapter 5	Points for Caution.....	11
5.1	Note on specifying path names.....	11
5.2	Other points for caution	11

Chapter 1 Target Devices

The target devices the CC-RL supports are listed on the Web site.

Please see the URL below.

CS+ Product Page:

<https://www.renesas.com/cs+>

Chapter 2 User's Manuals

Please read the following user's manuals along with this document.

Name	Document Number
CC-RL Compiler User's Manual	R20UT3123EJ0109
CS+ Integrated Development Environment User's Manual: CC-RL Build Tool Operation	R20UT3284EJ0108

Chapter 3 Keywords When Uninstalling the Product

There are two ways to uninstall this product.

- Use the integrated uninstaller from Renesas (uninstalls all CS+ components)
- Use the Windows uninstaller (only uninstalls this product)

To use the Windows uninstaller, select [CS+ CC-RL V1.09.00] from [Apps & features] from [Settings] of Windows or from [Programs and Features] of the control panel.

Chapter 4 Changes

This section describes changes to CC-RL from V1.08.00 to V1.09.00.

The features of the latter can only be used if the compiler is registered under the professional license.

They are indicated by **[Professional edition]** from here on.

4.1. Extensions to the checking of source code against MISRA-C:2012 rules **[Professional edition]**

The following rule numbers have been added as arguments of the -misra2012 option for checking source code against MISRA-C:2012 rules.

Required rules: **14.2** and **14.3**

Advisory rule: **8.13**

The following shows the number of MISRA-C:2012 rules which can be checked by each revision.

Classification of Rules: Number of Rules	V1.08.00	V1.09.00
Mandatory rules: 16	7	7
Required rules: 108	88	90
Advisory rules: 32	26	27
Total: 156	121	124

4.2. Writing the #pragma section directive within functions

The #pragma section directive can be written within functions.

The following target sections are individually specifiable: sections for static variables within functions, sections for string literals within functions, and sections for initial values for aggregate-type automatic variables.

4.3. C99 standard library functions

Support for standard library functions of the C99 language has newly been added and functionality for compliance with the C99 standard have been added to existing standard library functions as listed below.

scalbn	scalbnf	scalbnl	scalbln	scalblnf	scalblnl
nearbyint	nearbyintf	nearbyintl	rint	rintf	rintl
lrint	lrintf	lrintl	llrint	llrintf	llrintl
round	roundf	roundl	lround	lroundf	lroundl
llround	llroundf	llroundl	trunc	truncf	truncl
copysign	copysignf	copysignl	nan	nanf	nanl
fdim	fdimf	fdiml	fmax	fmaxf	fmaxl
fmin	fminf	fminl			
isgreater	isgreaterequal	isless	islessequal	islessgreater	isunordered
va_copy					

4.4. Allowing the specification of the same module names during the generation of a library

The `-allow_duplicate_module_name` option has been added.

Specifying this option allows the specification of the same module names during the generation of a library.

4.5.Improvement to code generated for loop processing

Code has been improved so that calculations which satisfy all the following conditions and need not be executed in a loop are executed outside the loop.

- Integer division is in a loop.
- The dividend and divisor for the integer division in the loop have fixed values.
- The divisor is a non-0 constant.

<Example of source code>

```
void update(unsigned int* array, unsigned n, unsigned value) {  
    unsigned i;  
    for (i = 0; i < n; ++i) {  
        if (i & 1 ) {  
            array[i] = value / 3;  
        }  
    }  
}
```

<Code output by CC-RL V1.08.00>

_update:

```

    push ax
    push de
    push bc
    movw ax, [sp+0x00]
    or a, x
    bz $.BB@LABEL@1_8

```

.BB@LABEL@1_1:

```

    movw ax, [sp+0x00]
    xor a, #0x80
    cmpw ax, #0x8002
    mov h, #0x00
    bc $.BB@LABEL@1_5

```

.BB@LABEL@1_2:

```

    movw ax, [sp+0x00]
    shrw ax, 0x01
    movw [sp+0x00], ax
    movw ax, [sp+0x04]
    addw ax, #0x0002
    movw hl, ax

```

.BB@LABEL@1_3:

```

    movw ax, [sp+0x02]
    movw de, #0x0003
    divhu
    movw [hl], ax
    movw ax, hl
    addw ax, #0x0004
    movw hl, ax
    movw ax, [sp+0x00]
    addw ax, #0xFFFF
    movw [sp+0x00], ax
    bnz $.BB@LABEL@1_3

```

.BB@LABEL@1_4:

```

    addw sp, #0x06
    ret

```

.BB@LABEL@1_5:

```

    mov a, h

```

<Code output by CC-RL V1.09.00>

_update:

```

    push hl
    push ax
    push bc
    pop hl
    movw ax, hl
    or a, x
    movw ax, de
    bz $.BB@LABEL@1_8

```

.BB@LABEL@1_1:

```

    movw de, #0x0003
    divhu
    movw [sp+0x02], ax
    movw ax, hl
    xor a, #0x80
    cmpw ax, #0x8002
    clrb b
    bc $.BB@LABEL@1_5

```

.BB@LABEL@1_2:

```

    movw ax, hl
    shrw ax, 0x01
    movw hl, ax
    movw ax, [sp+0x00]
    addw ax, #0x0002
    movw bc, ax

```

.BB@LABEL@1_3:

```

    movw ax, [sp+0x02]
    movw 0x0000[bc], ax
    movw ax, bc
    addw ax, #0x0004
    movw bc, ax
    movw ax, hl
    addw ax, #0xFFFF
    movw hl, ax
    bnz $.BB@LABEL@1_3

```

.BB@LABEL@1_4:

```

    addw sp, #0x04

```



```
        bf a.0, $.BB@LABEL@1_7
.BB@LABEL@1_6:
        movw ax, [sp+0x02]
        movw de, #0x0003
        divhu
        movw bc, ax
        movw ax, [sp+0x04]
        movw de, ax
        movw ax, bc
        movw [de], ax
.BB@LABEL@1_7:
        movw ax, [sp+0x04]
        addw ax, #0x0002
        movw [sp+0x04], ax
        inc h
        movw ax, [sp+0x00]
        addw ax, #0xFFFF
        movw [sp+0x00], ax
        bnz $.BB@LABEL@1_5
.BB@LABEL@1_8:
        addw sp, #0x06
        ret
```

```
        ret
.BB@LABEL@1_5:
        mov a, b
        bf a.0, $.BB@LABEL@1_7
.BB@LABEL@1_6:
        pop de
        push de
        movw ax, [sp+0x02]
        movw [de], ax
.BB@LABEL@1_7:
        movw ax, [sp+0x00]
        addw ax, #0x0002
        movw [sp+0x00], ax
        inc b
        movw ax, hl
        addw ax, #0xFFFF
        movw hl, ax
        bnz $.BB@LABEL@1_5
.BB@LABEL@1_8:
        addw sp, #0x04
        ret
```

4.6. Rectified point for caution

The following point for caution no longer applies. For details, refer to Tool News.

- Mathematical library function atan (CCRL#024)
- Using the -Oalias=ansi option (CCRL#025)

4.7. Other changes and improvements

Other major changes and improvements are described below.

- (a) Elimination of the output of messages on the results of MISRA-C checking to the standard header
Specifying the -misra2012 option so that source code was checked against the MISRA-C:2012 rules sometimes led to messages on the results of checking being output to the standard header. This has been corrected so that the messages are not output.
- (b) Correction of internal errors
Internal errors sometimes occurred in the build process in previous revisions. These errors have been corrected.

Chapter 5 Points for Caution

5.1 Note on specifying path names

Absolute paths that include drive letters or relative paths can be used as the path names for specifying input/output files or folders.

5.2 Other points for caution

Please refer to the user's manual for other points for caution regarding V1.09.00 of the CC-RL compiler.

All trademarks and registered trademarks are the property of their respective owners.

Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation or any other use of the circuits, software, and information in the design of your product or system. Renesas Electronics disclaims any and all liability for any losses and damages incurred by you or third parties arising from the use of these circuits, software, or information.
2. Renesas Electronics hereby expressly disclaims any warranties against and liability for infringement or any other claims involving patents, copyrights, or other intellectual property rights of third parties, by or arising from the use of Renesas Electronics products or technical information described in this document, including but not limited to, the product data, drawings, charts, programs, algorithms, and application examples.
3. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
4. You shall not alter, modify, copy, or reverse engineer any Renesas Electronics product, whether in whole or in part. Renesas Electronics disclaims any and all liability for any losses or damages incurred by you or third parties arising from such alteration, modification, copying or reverse engineering.
5. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The intended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.

"Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; industrial robots; etc.

"High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control (traffic lights); large-scale communication equipment; key financial terminal systems; safety control equipment; etc.

Unless expressly designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not intended or authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems; surgical implantations; etc.), or may cause serious property damage (space system; undersea repeaters; nuclear power control systems; aircraft control systems; key plant systems; military equipment; etc.). Renesas Electronics disclaims any and all liability for any damages or losses incurred by you or any third parties arising from the use of any Renesas Electronics product that is inconsistent with any Renesas Electronics data sheet, user's manual or other Renesas Electronics document.

6. When using Renesas Electronics products, refer to the latest product information (data sheets, user's manuals, application notes, "General Notes for Handling and Using Semiconductor Devices" in the reliability handbook, etc.), and ensure that usage conditions are within the ranges specified by Renesas Electronics with respect to maximum ratings, operating power supply voltage range, heat dissipation characteristics, installation, etc. Renesas Electronics disclaims any and all liability for any malfunctions, failure or accident arising out of the use of Renesas Electronics products outside of such specified ranges.
7. Although Renesas Electronics endeavors to improve the quality and reliability of Renesas Electronics products, semiconductor products have specific characteristics, such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Unless designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not subject to radiation resistance design. You are responsible for implementing safety measures to guard against the possibility of bodily injury, injury or damage caused by fire, and/or danger to the public in the event of a failure or malfunction of Renesas Electronics products, such as safety design for hardware and software, including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult and impractical, you are responsible for evaluating the safety of the final products or systems manufactured by you.
8. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. You are responsible for carefully and sufficiently investigating applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive, and using Renesas Electronics products in compliance with all these applicable laws and regulations. Renesas Electronics disclaims any and all liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
9. Renesas Electronics products and technologies shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You shall comply with any applicable export control laws and regulations promulgated and administered by the governments of any countries asserting jurisdiction over the parties or transactions.
10. It is the responsibility of the buyer or distributor of Renesas Electronics products, or any other party who distributes, disposes of, or otherwise sells or transfers the product to a third party, to notify such third party in advance of the contents and conditions set forth in this document.
11. This document shall not be reprinted, reproduced or duplicated in any form, in whole or in part, without prior written consent of Renesas Electronics.
12. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products.

(Note1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its directly or indirectly controlled subsidiaries.

(Note2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

(Rev.4.0-1 November 2017)

Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu,
Koto-ku, Tokyo 135-0061, Japan
www.renesas.com

Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.

Contact information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit:
www.renesas.com/contact/.