

DA9080-63FCBx Variant Overview

This document describes all the register default settings of the DA9080-63FCBx.

Contents

Contents1

Tables.....1

1. Terms and Definitions2

2. References.....2

3. Detailed Description2

4. Variant Table and Ordering Information.....3

Revision History4

Tables

Table 1. Register Settings DA9080-63FCBx2

Table 2. Variant Table3

1. Terms and Definitions

ADC	Analog to digital converter
CH<x>	Channel <x>, where x = 1 to 4
FCFN	Flip chip quad flat-pack no-lead (package)
LDO	Low drop out (regulator)
OTP	One time programmable
PG	Power good

2. References

[1] DA9080_Datasheet, Renesas Electronics.

Note 1 References are for the latest published version, unless otherwise indicated.

3. Detailed Description

Key settings:

- VCH1 = 3.30 V, VCH2 = 1.80 V, VCH3 = 1.10 V & VCH4 = 0.82 V
- VLDO = 3.30 V
- CH1 = SLOT4, CH2 = SLOT1, CH3 = SLOT3 & CH4 = SLOT2
- LDO = SLOT4
- ADC disabled
- CH<x> operates in AUTO mode, 2 MHz
- I2C standard speed. I2C slave address = 0x1B (7-bit)

Table 1. Register Settings DA9080-63FCBx

Register Address	Function	Default Value	Description
0x04	PMC_ADC_ENABLE	0x00	ADC disabled
0x05	PMC_CH_EN	0x1F	CH1, CH2, CH3, CH4 and LDO enabled
0x07	PMC_VOUT_BUCK1	0x3C	VCH1 = 3.30 V
0x08	PMC_VOUT_BUCK2	0x0F	VCH2 = 1.80 V
0x09	PMC_VOUT_BUCK3	0x28	VCH3 = 1.10 V
0x0A	PMC_VOUT_BUCK4	0x04	VCH4 = 0.82 V
0x0B	PMC_PHASE_INTERLEAVING	0x88	BUCK1_PHASE = 0° BUCK2_PHASE = 180° BUCK3_PHASE = 0° BUCK4_PHASE = 180°
0x0C	PMC_BUCK_SEQ_GRP	0x63	CH1 = SLOT4, CH2 = SLOT1 CH3 = SLOT3, CH4 = SLOT2
0x0D	PMC_LDO_SEQ_GRP	0x03	LDO = SLOT4
0x0E	PMC_PG1	0x08	CH3 assigned to PG1
0x0F	PMC_PG2	0x03	CH1 and LDO assigned to PG2
0x10	PMC_DISCHARGE	0x1F	CH<x> and LDO discharge enabled
0x62	OTP_CONFIG_ID	0x63	OTP variant number: DA9080-63FCBx

4. Variant Table and Ordering Information

Table 2. Variant Table

Part Number	Package	Size (mm)	Shipment Form	Pack Quantity
DA9080-63FCB2	32 FCQFN	5.0 x 5.0 by 0.5 mm pitch	Tape & Reel	6000
DA9080-63FCBC				1000

Revision History

Revision	Date	Description
1.0	Oct 24, 2024	First version.
2.0	Apr 04, 2025	Section 1 updated. Table 2 updated.

Status Definitions

Status	Definition
DRAFT	The content of this document is under review and subject to formal approval, which may result in modifications or additions.
APPROVED or unmarked	The content of this document has been approved for publication.

RoHS Compliance

Renesas Electronics' suppliers certify that its products are in compliance with the requirements of Directive 2011/65/EU of the European Parliament on the restriction of the use of certain hazardous substances in electrical and electronic equipment. RoHS certificates from our suppliers are available on request.

Important Notice and Disclaimer

RENESAS ELECTRONICS CORPORATION AND ITS SUBSIDIARIES ("RENESAS") PROVIDES TECHNICAL SPECIFICATIONS AND RELIABILITY DATA (INCLUDING DATASHEETS), DESIGN RESOURCES (INCLUDING REFERENCE DESIGNS), APPLICATION OR OTHER DESIGN ADVICE, WEB TOOLS, SAFETY INFORMATION, AND OTHER RESOURCES "AS IS" AND WITH ALL FAULTS, AND DISCLAIMS ALL WARRANTIES, EXPRESS OR IMPLIED, INCLUDING, WITHOUT LIMITATION, ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT OF THIRD PARTY INTELLECTUAL PROPERTY RIGHTS.

These resources are intended for developers skilled in the art designing with Renesas products. You are solely responsible for (1) selecting the appropriate products for your application, (2) designing, validating, and testing your application, and (3) ensuring your application meets applicable standards, and any other safety, security, or other requirements. These resources are subject to change without notice. Renesas grants you permission to use these resources only for development of an application that uses Renesas products. Other reproduction or use of these resources is strictly prohibited. No license is granted to any other Renesas intellectual property or to any third party intellectual property. Renesas disclaims responsibility for, and you will fully indemnify Renesas and its representatives against, any claims, damages, costs, losses, or liabilities arising out of your use of these resources. Renesas' products are provided only subject to Renesas' Terms and Conditions of Sale or other applicable terms agreed to in writing. No use of any Renesas resources expands or otherwise alters any applicable warranties or warranty disclaimers for these products.

© 2025 Renesas Electronics Corporation. All rights reserved.

(Rev.1.0 Mar 2020)

Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu
Koto-ku, Tokyo 135-0061, Japan
www.renesas.com

Contact Information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit:
<https://www.renesas.com/contact/>

Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.