

# UPC277GR, UPC277MP, UPC393GR

## Small Package Single Power Supply Dual Comparator

### DESCRIPTION

UPC277GR-9LG, UPC277MP-KAA, UPC393GR-9LG are dual comparators designed to operate under single power supply. Features include low-voltage operation, common-mode input voltage range from  $V^-$  (GND) level, open collector output, and low current consumption. Furthermore, these products can operate on a split power supply and used widely for various voltage comparison application.




Depending on the usage and operating ambient temperature range, the UPC277GR-9LG, UPC277MP-KAA are designed for extended temperature and suited for wide operating ambient temperature application, while UPC393GR-9LG are designed for general purposes application.

In addition, compatible DC parameter selection for the comparators also available.

Along with this series of lineup, the quad type comparators, UPC177GR-9LG and UPC339GR-9LG with the same circuit configuration are also available.

### FEATURES

- Input Offset Voltage  $\pm 2$  mV (TYP.)
- Input Bias Current 17 nA (TYP.)
- Voltage Gain 200000 (TYP.)
- Pulse Response Time 1.8  $\mu$ s (TYP.)
- Output Sink Current 16 mA (TYP.)
- A wired OR is possible as the output is an open collector.
- Low Voltage Operation  $V^+ - V^- : +2 \sim +32$  V
- Small Package (The mounting area is reduced by 40% or 65% compared to conventional 8-pin plastic SOP, as shown in the table below)

Package	Standard SOP	TSSOP	MSOP
Part Number	UPC277G2, UPC393G2	UPC277GR-9LG, UPC393GR-9LG	UPC277MP-KAA
Outline Comparison	Unit : mm 	Unit : mm 	Unit : mm 
(Mounting Area Ratio)	( 100 % )	( 60 % )	( 35 % )


### ORDERING INFORMATION

Order Name <sup>(1)</sup>	Selected Grade	Package
UPC277GR-9LG-A	Standard	8-pin plastic TSSOP ( 5.72 mm ( 225 ) )
UPC277GR(5)-9LG-A	DC parameter selection	8-pin plastic TSSOP ( 5.72 mm ( 225 ) )
UPC277MP-KAA-A	Standard	8-pin plastic MSOP ( 2.80 × 2.95 mm )
UPC393GR-9LG-A	Standard	8-pin plastic TSSOP ( 5.72 mm ( 225 ) )
UPC393GR(5)-9LG-A	DC parameter selection	8-pin plastic TSSOP ( 5.72 mm ( 225 ) )


(1) Order names containing E1 or E2 indicate that the packaging format is embossed taping.

Pin 1 of E1 is on draw-out side, and pin 1 of E2 is at take-up side.

**EQUIVALENT CIRCUIT (1/2 CIRCUIT)**



**PIN CONFIGURATION (Marking side)**



**ABSOLUTE MAXIMUM RATINGS (T<sub>A</sub> = 25 °C)**

Parameter	Symbol	UPC277GR-9LG UPC277GR(5)-9LG	UPC277MP-KAA	UPC393GR-9LG UPC393GR(5)-9LG	Unit
Power Supply Voltage <sup>Note 1</sup>	V <sup>+</sup> - V <sup>-</sup>	-0.3 ~ +36			V
Differential Input Voltage	V <sub>ID</sub>	±36			V
Input Voltage <sup>Note 2</sup>	V <sub>I</sub>	V <sup>-</sup> -0.3 ~ V <sup>-</sup> +36			V
Output Applied Voltage <sup>Note 3</sup>	V <sub>O</sub>	V <sup>-</sup> -0.3 ~ V <sup>-</sup> +36			V
Total Power Dissipation <sup>Note 4</sup>	P <sub>T</sub>	440			mW
Output Short Circuit Duration (vs. GND) <sup>Note 5</sup>	t <sub>s</sub>	Indefinite			s
Operating Ambient Temperature	T <sub>A</sub>	-40 ~ +125		-40 ~ +85	°C
Storage Temperature	T <sub>stg</sub>	-55 ~ +150		-55 ~ +125	°C

- [Note]**
- Note that reverse connections of the power supply may damage the ICs.
  - The allowable input voltage range without damaging or destructing the device. Independent to power supply voltage range.  
Do not apply voltage of V<sup>-</sup> (GND) - 0.3 V or less.  
Note that the comparator will operate normally when the input voltage applied is within the common mode input voltage range.
  - The input voltage range that can be applied to the output pin externally without deteriorating or damaging the device characteristic. The permitted input voltage that can be applied regardless of the power supply voltage. This specification also includes precaution during transition state such as ON/OFF, etc.
  - This is the value when the glass epoxy substrate (size: 100 mm x 100 mm, thickness: 1 mm, 15 % of the substrate area where only one side is copper foiled is filling wired) is mounted.  
Note that restrictions will be made to the following conditions for each product, and the de-rating ratio depending on the operating ambient temperature.  
UPC277GR-9LG : De-rate -5.5 mW/°C when T<sub>A</sub> > 69 °C.  
(Junction - ambient thermal resistance R<sub>th(J-A)</sub> = 183 °C /W)  
UPC277MP-KAA : De-rate -4.8 mW/°C when T<sub>A</sub> > 58 °C.  
(Junction - ambient thermal resistance R<sub>th(J-A)</sub> = 208 °C v/W)  
UPC393GR-9LG : De-rate -5.5 mW/°C when T<sub>A</sub> > 44 °C.  
(Junction - ambient thermal resistance R<sub>th(J-A)</sub> = 183 °C /W)
  - Short circuit at the V<sup>+</sup> side may destroy the IC. Please use the total loss and the de-rating factor of Note 4.

**RECOMMENDED OPERATING CONDITIONS**

Parameter	Symbol	MIN.	TYP.	MAX.	Unit
Power Supply Voltage (Dual Supply)	$V^{\pm}$	$\pm 1$		$\pm 16$	V
Power Supply Voltage ( $V^- = \text{GND}$ )	$V^+$	+2		+32	V

**ELECTRICAL CHARACTERISTICS**UPC277GR-9LG, UPC277MP-KAA, UPC393GR-9LG ( $T_A = 25\text{ }^{\circ}\text{C}$ ,  $V^+ = +5\text{ V}$ ,  $V^- = \text{GND}$ )

Parameter	Symbol	MIN.	TYP.	MAX.	Unit	Test Condition
Input Offset Voltage	$V_{IO}$		$\pm 2$	$\pm 5$	mV	$V_O = 1.4\text{ V}$ , $V_{REF} = 1.4\text{ V}$ , $R_S = 0\ \Omega$
Input Offset Current	$I_{IO}$		$\pm 5$	$\pm 50$	nA	$V_O = 1.4\text{ V}$
Input Bias Current <sup>Note 6</sup>	$I_B$		17	250	nA	$V_O = 1.4\text{ V}$
Large Signal Voltage Gain	$A_v$		200000			$R_L = 15\text{ k}\Omega$
Circuit Current <sup>Note 7</sup>	$I_{CC}$		0.6	1	mA	$R_L = \infty$ , $I_O = 0\text{ A}$
Common Mode Input Voltage Range	$V_{ICM}$	0		$V^+ - 1.5$	V	
Output Saturation Voltage	$V_{OL}$		0.2	0.4	V	$V_{IN(-)} = +1\text{ V}$ , $V_{IN(+)} = 0\text{ V}$ , $I_{O\text{ SINK}} = 4\text{ mA}$
Output Sink Current	$I_{O\text{ SINK}}$	6	16		mA	$V_{IN(-)} = +1\text{ V}$ , $V_{IN(+)} = 0\text{ V}$ , $V_O \leq 1.5\text{ V}$
Output Leakage Current	$I_{O\text{ LEAK}}$		0.1		nA	$V_{IN(+)} = +1\text{ V}$ , $V_{IN(-)} = 0\text{ V}$ , $V_O = 5\text{ V}$
Pulse Response Time <sup>Note 8</sup>			1.8		$\mu\text{s}$	$R_L = 5.1\text{ k}\Omega$ , $V_{RL} = 5\text{ V}$

UPC277GR(5)-9LG, UPC393GR(5)-9LG ( $T_A = 25\text{ }^{\circ}\text{C}$ ,  $V^+ = +5\text{ V}$ ,  $V^- = \text{GND}$ )

Parameter	Symbol	MIN.	TYP.	MAX.	Unit	Test Condition
Input Offset Voltage	$V_{IO}$		$\pm 2$	$\pm 2.5$	mV	$V_O = 1.4\text{ V}$ , $V_{REF} = 1.4\text{ V}$ , $R_S = 0\ \Omega$
Input Offset Current	$I_{IO}$		$\pm 5$	$\pm 50$	nA	$V_O = 1.4\text{ V}$
Input Bias Current <sup>Note 6</sup>	$I_B$		17	60	nA	$V_O = 1.4\text{ V}$
Large Signal Voltage Gain	$A_v$		200000			$R_L = 15\text{ k}\Omega$
Circuit Current <sup>Note 7</sup>	$I_{CC}$		0.6	0.8	mA	$R_L = \infty$ , $I_O = 0\text{ A}$
Common Mode Input Voltage Range	$V_{ICM}$	0		$V^+ - 1.4$	V	
Output Saturation Voltage	$V_{OL1}$			0.2	V	$V_{IN(-)} = +1\text{ V}$ , $V_{IN(+)} = 0\text{ V}$ , $I_{O\text{ SINK}} = 4\text{ mA}$
	$V_{OL2}$			1.5	V	$V_{IN(-)} = +1\text{ V}$ , $V_{IN(+)} = 0\text{ V}$ , $I_{O\text{ SINK}} = 10\text{ mA}$
Output Sink Current	$I_{O\text{ SINK}}$	10	16		mA	$V_{IN(-)} = +1\text{ V}$ , $V_{IN(+)} = 0\text{ V}$ , $V_O \leq 1.5\text{ V}$
Output Leakage Current	$I_{O\text{ LEAK}}$		0.1	100	nA	$V_{IN(+)} = +1\text{ V}$ , $V_{IN(-)} = 0\text{ V}$ , $V_O = 5\text{ V}$
Pulse Response Time <sup>Note 8</sup>			1.8		$\mu\text{s}$	$R_L = 5.1\text{ k}\Omega$ , $V_{RL} = 5\text{ V}$

**[Note]** 6. The current flow direction of the input bias is out from the IC because the first stage of the IC composed of PNP transistor.

The current value is the value when the differential amplified circuit of the input stage is balanced.  
When the comparator is active, twice the amount of current will flow to the pin with lower potential.


7. Current flowing through the internal circuit. This current flow regardless of the channel used.

8. Values when the input amplitude is 100 mV and the overdrive is 5 mV.

Increasing the overdrive can shorten the response time.


## TYPICAL APPLICATION CIRCUIT EXAMPLE

### EXAMPLE 1



$$V_{REF} : V^- \sim V^+ - 1.5 [V]$$

### EXAMPLE 2 (With Hysteresis)









- Threshold Voltage



$$V_{TH (High)} \doteq V_{REF} + \frac{R_1}{R_L + R_2 + R_1} (V_{RL} - V_{REF})$$

$$V_{TH (Low)} \doteq V_{REF} - \frac{R_1}{R_1 + R_2} (V_{REF} - V_{OL})$$

$$(V_{RL} > V_{REF} > V_{OL})$$

**TYPICAL PERFORMANCE CHARACTERISTICS (T<sub>A</sub> = 25 °C, TYP.) (Reference value)**






## USE WITH PRECAUTIONS

- **Managing unused circuits**

If there is an unused circuit, the following connection is recommended.

Process example of unused circuits



- **Ratings of input/output pin voltage**

When the voltage of input/output pin exceeds the absolute maximum rating, the parasitic diode within the IC may conduct, causing characteristics degradation or damage. In addition, if the input pin is lower than  $V^-$ , or the output pin exceeds the power supply voltage, it is recommended to make a clamping circuit using a diode with low forward voltage (e.g.: Schottky diode) as protection.

- **Range of common-mode input voltage**

When the supply voltage does not meet the condition of electrical characteristics, the range of common-mode input voltage is as follows.

$$V_{ICM} \text{ (TYP.)}: V^- \sim V^+ - 1.5 \text{ [V]} \text{ (} T_A = 25 \text{ } ^\circ\text{C)}$$

During designing, do include some tolerance by considering temperature characteristics etc.

- **Range of input current**

The Input Bias Current [ $I_B$ ] specified in the electrical characteristics table, is the average value of current flowing through the +input terminal [ $I_N$ ] and the current flowing through the -input terminal [ $I_I$ ] in the balanced state of the differential amplifier circuit of the input stage (with negative feedback).

Therefore, since the differential amplifier circuit of the input stage is not balanced during comparison operation (in the case of comparator operation), the input current flows twice as much towards the low potential terminal.


- **Handling of ICs**

When stress is added to the ICs due to warpage or bending of a board, the characteristic may fluctuates due to piezoelectric (piezo) effect. Therefore, pay attention to warpage or bending of a board.

## PACKAGE DRAWINGS

### 8-PIN PLASTIC TSSOP

JEITA Package code	RENESAS code	Previous code	MASS(TYP.) [g]
P-TSSOP8-0225-0.65	PTSP0008JD-A	P8GR-65-9LG	—



#### NOTE


Each lead centerline is located within 0.10 mm of its true position at maximum material condition.

(Unit : mm)

ITEM	MILLIMETERS
D	3.15 ±0.15
D1	3.00 ±0.10
E	4.40 ±0.10
HE	6.40 ±0.20
A	1.20 MAX.
A1	0.10 ±0.05
A2	1.00 ±0.05
A3	0.25
b	0.24 <sup>+0.06</sup> <sub>-0.05</sub>
c	0.145 ±0.055
L	0.5
Lp	0.60 ±0.15
L1	1.00 ±0.20
θ	3° <sup>+5°</sup> <sub>-3°</sub>
e	0.65
x	0.10
y	0.10
ZD	0.60

8-PIN PLASTIC MSOP

JEITA Package Code	RENESAS Code	MASS (TYP.) [g]
P-VSSOP8-2.75×2.8-0.65	PVSP0008JA-A	0.02[g]



NOTE)  
 1. DIMENSIONS "\*1"  
 DO NOT INCLUDE MOLD FLASH.  
 2. EACH LEAD CENTERLINE IS LOCATED WITHIN 0.10 MM OF  
 ITS TRUE POSITION AT MAXIMUM MATERIAL CONDITION.

(UNIT:mm)

ITEM	DIMENSIONS
D	2.75
D1	2.95±0.20
E	2.80
HE	4.00±0.30
e	0.65
b	0.20 <sup>+0.10</sup> <sub>-0.05</sub>
A	1.00MAX
A1	0.05±0.05
A2	0.85±0.10
A3	0.25
L1	0.60±0.20
c	0.13 <sup>+0.10</sup> <sub>-0.05</sub>
Lp	0.37±0.12
x	0.10
y	0.10
θ	7±7°
ZD	0.50

## Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation or any other use of the circuits, software, and information in the design of your product or system. Renesas Electronics disclaims any and all liability for any losses and damages incurred by you or third parties arising from the use of these circuits, software, or information.
2. Renesas Electronics hereby expressly disclaims any warranties against and liability for infringement or any other claims involving patents, copyrights, or other intellectual property rights of third parties, by or arising from the use of Renesas Electronics products or technical information described in this document, including but not limited to, the product data, drawings, charts, programs, algorithms, and application examples.
3. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
4. You shall be responsible for determining what licenses are required from any third parties, and obtaining such licenses for the lawful import, export, manufacture, sales, utilization, distribution or other disposal of any products incorporating Renesas Electronics products, if required.
5. You shall not alter, modify, copy, or reverse engineer any Renesas Electronics product, whether in whole or in part. Renesas Electronics disclaims any and all liability for any losses or damages incurred by you or third parties arising from such alteration, modification, copying or reverse engineering.
6. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The intended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.
  - "Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; industrial robots; etc.
  - "High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control (traffic lights); large-scale communication equipment; key financial terminal systems; safety control equipment; etc.

Unless expressly designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not intended or authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems; surgical implantations; etc.), or may cause serious property damage (space system; undersea repeaters; nuclear power control systems; aircraft control systems; key plant systems; military equipment; etc.). Renesas Electronics disclaims any and all liability for any damages or losses incurred by you or any third parties arising from the use of any Renesas Electronics product that is inconsistent with any Renesas Electronics data sheet, user's manual or other Renesas Electronics document.
7. No semiconductor product is absolutely secure. Notwithstanding any security measures or features that may be implemented in Renesas Electronics hardware or software products, Renesas Electronics shall have absolutely no liability arising out of any vulnerability or security breach, including but not limited to any unauthorized access to or use of a Renesas Electronics product or a system that uses a Renesas Electronics product. RENESAS ELECTRONICS DOES NOT WARRANT OR GUARANTEE THAT RENESAS ELECTRONICS PRODUCTS, OR ANY SYSTEMS CREATED USING RENESAS ELECTRONICS PRODUCTS WILL BE INVULNERABLE OR FREE FROM CORRUPTION, ATTACK, VIRUSES, INTERFERENCE, HACKING, DATA LOSS OR THEFT, OR OTHER SECURITY INTRUSION ("Vulnerability Issues"). RENESAS ELECTRONICS DISCLAIMS ANY AND ALL RESPONSIBILITY OR LIABILITY ARISING FROM OR RELATED TO ANY VULNERABILITY ISSUES. FURTHERMORE, TO THE EXTENT PERMITTED BY APPLICABLE LAW, RENESAS ELECTRONICS DISCLAIMS ANY AND ALL WARRANTIES, EXPRESS OR IMPLIED, WITH RESPECT TO THIS DOCUMENT AND ANY RELATED OR ACCOMPANYING SOFTWARE OR HARDWARE, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY, OR FITNESS FOR A PARTICULAR PURPOSE.
8. When using Renesas Electronics products, refer to the latest product information (data sheets, user's manuals, application notes, "General Notes for Handling and Using Semiconductor Devices" in the reliability handbook, etc.), and ensure that usage conditions are within the ranges specified by Renesas Electronics with respect to maximum ratings, operating power supply voltage range, heat dissipation characteristics, installation, etc. Renesas Electronics disclaims any and all liability for any malfunctions, failure or accident arising out of the use of Renesas Electronics products outside of such specified ranges.
9. Although Renesas Electronics endeavors to improve the quality and reliability of Renesas Electronics products, semiconductor products have specific characteristics, such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Unless designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not subject to radiation resistance design. You are responsible for implementing safety measures to guard against the possibility of bodily injury, injury or damage caused by fire, and/or danger to the public in the event of a failure or malfunction of Renesas Electronics products, such as safety design for hardware and software, including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult and impractical, you are responsible for evaluating the safety of the final products or systems manufactured by you.
10. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. You are responsible for carefully and sufficiently investigating applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive, and using Renesas Electronics products in compliance with all these applicable laws and regulations. Renesas Electronics disclaims any and all liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
11. Renesas Electronics products and technologies shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You shall comply with any applicable export control laws and regulations promulgated and administered by the governments of any countries asserting jurisdiction over the parties or transactions.
12. It is the responsibility of the buyer or distributor of Renesas Electronics products, or any other party who distributes, disposes of, or otherwise sells or transfers the product to a third party, to notify such third party in advance of the contents and conditions set forth in this document.
13. This document shall not be reprinted, reproduced or duplicated in any form, in whole or in part, without prior written consent of Renesas Electronics.
14. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products.

(Note1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its directly or indirectly controlled subsidiaries.

(Note2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

(Rev.5.0-1 October 2020)

## Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu,  
Koto-ku, Tokyo 135-0061, Japan  
[www.renesas.com](http://www.renesas.com)

## Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.

## Contact information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit:  
[www.renesas.com/contact/](http://www.renesas.com/contact/).