

UPC835

Low Power, High Stability, Low Offset Voltage

J-FET Input Dual Operational Amplifier

DESCRIPTION

The UPC835 is the higher version of UPC832 and 4062, the J-FET input operational amplifiers, in stability and accuracy. The UPC835 is a J-FET input dual operational amplifier which realizes both low power consumption and high stability, by adopting a high speed PNP transistor of $f_T = 300$ MHz on its output stage.

In addition, despite its J-FET input, the UPC835 realizes low offset voltage characteristics that eclipses conventional general operational amplifiers, by using a resistance trimming system, the proven method for our high accuracy operational amplifier and high accuracy reference voltage.

The UPC835 is ideal for use in measurement instruments and control instruments, which especially requires the stability during capacitive load connections.

FEATURES


- Input Offset Voltage ±3 mV MAX.
- Slew Rate 5.5 V/μs (TYP.)
- Unity Gain Frequency 2.8 MHz (TYP.)
- Low Power $I_{CC} \leq 2.2$ mA MAX.
(Reduces circuit currents while maintaining relatively high slew rate and bandwidth)
- High stability is secured to capacitive loads
(Capacitive Load at 4000 pF, AV = +1)
- Built-In Phase Compensation Circuit
- Small package
The whole size of the package is downsized by 30 to 40% compared with a standard SOP contour, by using a TSSOP (3 x 3 mm² body) package

ORDERING INFORMATION


Order Name	Package	Packing Type
UPC835MN-KAA-E1-AT ^{Note}	8-pin plastic TSSOP (3 x 3)	<ul style="list-style-type: none"> • 12mm wide embossed taping • Pin 1 at draw-out side • 4000 p/reel
UPC835MN-KAA-E2-AT ^{Note}	8-pin plastic TSSOP (3 x 3)	<ul style="list-style-type: none"> • 12mm wide embossed taping • Pin 1 at reel side • 4000 p/reel

Note Pb-free (This product does not contain Pb in the external electrode and other parts.)

EQUIVALENT CIRCUIT (1/2 Circuit)



PIN CONFIGURATION (Top View)



ABSOLUTE MAXIMUM RATINGS (TA = 25 °C, unless otherwise specified)

Parameter	Symbol	UPC835	Unit
Supply Voltage ^{Note1}	V ⁺ - V ⁻	-0.3 ~ +36	V
Differential Input Voltage	V _{ID}	±30	V
Input Voltage ^{Note 2}	V _I	V ⁻ -0.3 ~ V ⁺ +0.3	V
Output Applied Voltage ^{Note3}	V _O	V ⁻ -0.3 ~ V ⁺ +0.3	V
Total Power Dissipation ^{Note4}	P _T	350	mW
Output Short Circuit Duration ^{Note5}		Indefinite	s
Operating Ambient Temperature	T _A	-40 ~ +85	°C
Storage Temperature	T _{stg}	-55 ~ +125	°C

- [Notes]**
- Note that reverse connections of the power supply may damage the ICs.
 - The input terminal must be applied within the input voltage range to avoid deteriorating or damaging the device characteristic. Do not exceed the ratings including during transition state such as ON/OFF, etc. The Op-Amp input voltage must operate within the electrical characteristics range of input common-mode voltage.
 - The output terminal must be applied within the output voltage range to avoid deteriorating or damaging the device characteristic. Do not exceed the ratings including during transition state such as ON/OFF, etc. The Op-Amp output voltage must operate within the electrical characteristics range of maximum output voltage.
 - This is the value when T_A ≤ 59°C during loading a glass epoxy substrate (size: 100 mm x 100 mm, thickness: 1 mm, filling wiring of 15% of the substrate only on the one side of copper foil). When T_A > 59°C, conduct a derating in -5.4 mW/°C. The heat resistance between a junction and ambient air under the same condition is R_{th(J-A)} = 187°C /W.
 - Pay careful attention to the total power dissipation not to exceed the absolute maximum ratings, Note 4.

Caution Product quality may suffer if the absolute maximum rating is exceeded even momentarily for any parameter. That is, the absolute maximum ratings are rated values at which the product is on the verge of suffering physical damage, and therefore the product must be used under conditions that ensure that the absolute maximum ratings are not exceeded.

RECOMMENDED OPERATING CONDITIONS

Parameter	Symbol	MIN.	TYP.	MAX.	Unit
Power Supply Voltage	V [±]	±5		±16	V
Output Current	I _o			±6	mA
Load Capacitance (When A _v = +1)	C _L			4000 ^{Note6}	pF

[Note] 6. This is the value when the feedback resistor (R_f) = 0 Ω. The higher the R_f value, the more likely it is to oscillate due to the influence of the input capacitance. So connect a capacitor of about 100 pF in parallel with R_f.







ELECTRICAL CHARACTERISTICS ($T_A = 25\text{ }^\circ\text{C}$, $V^\pm = \pm 15\text{ V}$, unless otherwise specified)





Parameter	Symbol	MIN.	TYP.	MAX.	Unit	Test Condition
Input Offset Voltage	V_{IO}		± 1.5	± 3	mV	$R_s \leq 50\ \Omega$
Input Offset Current	I_{IO}		± 25	± 100	pA	
Input Bias Current ^{Note7}	I_B		50	200	pA	
Large Signal Voltage Gain	A_V	25000	200000			$R_L \geq 2\text{ k}\Omega$, $V_O = \pm 10\text{ V}$
Circuit Current ^{Note8}	I_{CC}		1.4	2.2	mA	$I_O = 0\text{ A}$
Common Mode Rejection Ratio	CMR	70	80		dB	
Supply Voltage Rejection Ratio	SVR	70	85		dB	
Output Voltage Swing	V_{om}	± 12	+14.0 -13.3		V	$R_L \geq 10\text{ k}\Omega$
Output Voltage Swing	V_{om}	± 10	+13.5 -12.8		V	$R_L \geq 2\text{ k}\Omega$
Common Model Input Voltage Range	V_{ICM}	+11.7 -11.0	+15 -12		V	
Slew Rate	SR		5.5		V/ μ s	$A_V = 1$
Unity Gain Frequency	f_{unity}		2.8		MHz	
Input Equivalent Noise Voltage Density	e_n		25		nV/ $\sqrt{\text{Hz}}$	$R_s = 100\ \Omega$, $f = 1\text{ kHz}$
Channel Separation			120		dB	
Average V_{IO} Temperature Drift	$\Delta V_{IO}/\Delta T$		± 7		$\mu\text{V}/^\circ\text{C}$	$T_A = -20 \sim +70\text{ }^\circ\text{C}$

- [Note] 7.** Input bias currents flow into IC, because each currents are base current to Pch J-FET on input stage. When $T_J = 25\text{ }^\circ\text{C}$ or more, this figure exponentially grows along with a rise of temperature.
8. This current flows irrespective of the existence of use.


Caution Special attention is required for insulation between pins on a board, since the UPC835 has a high-input impedance characteristic..

**TYPICAL PERFORMANCE CHARACTERISTICS (T_A = 25°C, unless otherwise specified)
(Reference value)**






PULSE RESPONSE I
 $(V^{\pm} = \pm 15\text{ V}, A_V = +1, R_L = 2\text{ k}\Omega, C_L = 100\text{ pF})$



PULSE RESPONSE II
 $(V^{\pm} = \pm 15\text{ V}, A_V = +1, R_L = 2\text{ k}\Omega, C_L = 4000\text{ pF})$




PRECAUTIONS FOR USE

- **Managing unused circuits**

If there is an unused circuit, the following connection is recommended.

Example of unused circuit process



Remark Note in this example, an intermediate voltage of V^+ and V^- is applied.

- **Power Supply (Dual Power Supply / Single Power Supply)**

Operational amplifiers operate when a given voltage is applied to between V^+ and V^- . Therefore, they can operate with a single power supply ($V^- = \text{GND}$). However, since input/output around the GND is impossible with the single power supply, it is required to pay attention to the common-mode input voltage range and the maximum output voltage when using them.

- **Ratings of input/output pin voltage**

When the voltage of input/output pin exceeds the absolute maximum rating, it may cause degradation of characteristics or damages, by a conduction of a parasitic diode within an IC. In addition, when the input pin may be lower than V^- , or the output pin may exceed the supply voltage, it is recommended to make a clamp circuit by a diode whose forward voltage is low (e.g.: Schottky diode) for protection.

- **Range of common-mode input voltage**

When the supply voltage does not meet the condition of electrical characteristics, the range of common-mode input voltage is as follows.

$$V_{ICM} (\text{TYP.}) : V^- + 3 \sim V^+ [\text{V}] (T_A = 25^\circ\text{C}).$$

During designing, consider variations in characteristics and temperature characteristics for use with allowance.

- **Maximum output voltage**

The range of the TYP. value of the maximum output voltage when the supply voltage does not meet the condition of electrical characteristics is as follows:

$$V_{om+} (\text{TYP.}) : V^+ - 1 [\text{V}] (T_A = 25^\circ\text{C}, R_L \geq 10 \text{ k}\Omega), V_{om-} (\text{TYP.}) : V^- + 1.7 [\text{V}] (T_A = 25^\circ\text{C}, R_L \geq 10 \text{ k}\Omega)$$




During designing, consider variations in characteristics and temperature characteristics for use with allowance. In addition, note that the output voltage range ($V_{om+} - V_{om-}$) becomes narrow when the output current increases.

- **Handling of ICs**

When stress is added to ICs due to warpage or bending of a board, the characteristic fluctuates due to piezoelectric effect. Therefore, pay attention to warpage or bending of a board.

PACKAGE DRAWINGS

8-PIN PLASTIC TSSOP (3x3)



(UNIT:mm)

ITEM	DIMENSIONS
D	3.00
E	3.00
f	0.20
HE	4.90
t	0.20
e	0.65
bp	0.25 to 0.38
A1	0.10±0.05
A	1.10 MAX.
A2	0.85±0.10
A3	0.25
L1	0.95
c	0.13 to 0.23
Lp	0.55±0.15
x	0.10
y	0.10
θ	3°+5° -3°

P8MN-65-KAA-1

Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation or any other use of the circuits, software, and information in the design of your product or system. Renesas Electronics disclaims any and all liability for any losses and damages incurred by you or third parties arising from the use of these circuits, software, or information.
2. Renesas Electronics hereby expressly disclaims any warranties against and liability for infringement or any other claims involving patents, copyrights, or other intellectual property rights of third parties, by or arising from the use of Renesas Electronics products or technical information described in this document, including but not limited to, the product data, drawings, charts, programs, algorithms, and application examples.
3. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
4. You shall be responsible for determining what licenses are required from any third parties, and obtaining such licenses for the lawful import, export, manufacture, sales, utilization, distribution or other disposal of any products incorporating Renesas Electronics products, if required.
5. You shall not alter, modify, copy, or reverse engineer any Renesas Electronics product, whether in whole or in part. Renesas Electronics disclaims any and all liability for any losses or damages incurred by you or third parties arising from such alteration, modification, copying or reverse engineering.
6. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The intended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.
 - "Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; industrial robots; etc.
 - "High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control (traffic lights); large-scale communication equipment; key financial terminal systems; safety control equipment; etc.
7. Unless expressly designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not intended or authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems; surgical implantations; etc.), or may cause serious property damage (space system; undersea repeaters; nuclear power control systems; aircraft control systems; key plant systems; military equipment; etc.). Renesas Electronics disclaims any and all liability for any damages or losses incurred by you or any third parties arising from the use of any Renesas Electronics product that is inconsistent with any Renesas Electronics data sheet, user's manual or other Renesas Electronics document.
7. No semiconductor product is absolutely secure. Notwithstanding any security measures or features that may be implemented in Renesas Electronics hardware or software products, Renesas Electronics shall have absolutely no liability arising out of any vulnerability or security breach, including but not limited to any unauthorized access to or use of a Renesas Electronics product or a system that uses a Renesas Electronics product. RENESAS ELECTRONICS DOES NOT WARRANT OR GUARANTEE THAT RENESAS ELECTRONICS PRODUCTS, OR ANY SYSTEMS CREATED USING RENESAS ELECTRONICS PRODUCTS WILL BE INVULNERABLE OR FREE FROM CORRUPTION, ATTACK, VIRUSES, INTERFERENCE, HACKING, DATA LOSS OR THEFT, OR OTHER SECURITY INTRUSION ("Vulnerability Issues"). RENESAS ELECTRONICS DISCLAIMS ANY AND ALL RESPONSIBILITY OR LIABILITY ARISING FROM OR RELATED TO ANY VULNERABILITY ISSUES. FURTHERMORE, TO THE EXTENT PERMITTED BY APPLICABLE LAW, RENESAS ELECTRONICS DISCLAIMS ANY AND ALL WARRANTIES, EXPRESS OR IMPLIED, WITH RESPECT TO THIS DOCUMENT AND ANY RELATED OR ACCOMPANYING SOFTWARE OR HARDWARE, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY, OR FITNESS FOR A PARTICULAR PURPOSE.
8. When using Renesas Electronics products, refer to the latest product information (data sheets, user's manuals, application notes, "General Notes for Handling and Using Semiconductor Devices" in the reliability handbook, etc.), and ensure that usage conditions are within the ranges specified by Renesas Electronics with respect to maximum ratings, operating power supply voltage range, heat dissipation characteristics, installation, etc. Renesas Electronics disclaims any and all liability for any malfunctions, failure or accident arising out of the use of Renesas Electronics products outside of such specified ranges.
9. Although Renesas Electronics endeavors to improve the quality and reliability of Renesas Electronics products, semiconductor products have specific characteristics, such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Unless designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not subject to radiation resistance design. You are responsible for implementing safety measures to guard against the possibility of bodily injury, injury or damage caused by fire, and/or danger to the public in the event of a failure or malfunction of Renesas Electronics products, such as safety design for hardware and software, including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult and impractical, you are responsible for evaluating the safety of the final products or systems manufactured by you.
10. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. You are responsible for carefully and sufficiently investigating applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive, and using Renesas Electronics products in compliance with all these applicable laws and regulations. Renesas Electronics disclaims any and all liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
11. Renesas Electronics products and technologies shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You shall comply with any applicable export control laws and regulations promulgated and administered by the governments of any countries asserting jurisdiction over the parties or transactions.
12. It is the responsibility of the buyer or distributor of Renesas Electronics products, or any other party who distributes, disposes of, or otherwise sells or transfers the product to a third party, to notify such third party in advance of the contents and conditions set forth in this document.
13. This document shall not be reprinted, reproduced or duplicated in any form, in whole or in part, without prior written consent of Renesas Electronics.
14. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products.

(Note1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its directly or indirectly controlled subsidiaries.

(Note2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

(Rev.5.0-1 October 2020)

Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu,
Koto-ku, Tokyo 135-0061, Japan
www.renesas.com

Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.

Contact information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit:
www.renesas.com/contact/.