

Linux Interface Specification Device Driver USB3.2 Host

User's Manual: Software

RZ/V2N Group and RZ/G3E Group

All information contained in these materials, including products and product specifications, represents information on the product at the time of publication and is subject to change by Renesas Electronics Corp. without notice. Please review the latest information published by Renesas Electronics Corp. through various means, including the Renesas Electronics Corp. website (<http://www.renesas.com>).

Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation or any other use of the circuits, software, and information in the design of your product or system. Renesas Electronics disclaims any and all liability for any losses and damages incurred by you or third parties arising from the use of these circuits, software, or information.
2. Renesas Electronics hereby expressly disclaims any warranties against and liability for infringement or any other claims involving patents, copyrights, or other intellectual property rights of third parties, by or arising from the use of Renesas Electronics products or technical information described in this document, including but not limited to, the product data, drawings, charts, programs, algorithms, and application examples.
3. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
4. You shall be responsible for determining what licenses are required from any third parties, and obtaining such licenses for the lawful import, export, manufacture, sales, utilization, distribution or other disposal of any products incorporating Renesas Electronics products, if required.
5. You shall not alter, modify, copy, or reverse engineer any Renesas Electronics product, whether in whole or in part. Renesas Electronics disclaims any and all liability for any losses or damages incurred by you or third parties arising from such alteration, modification, copying or reverse engineering.
6. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The intended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.

"Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; industrial robots; etc.

"High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control (traffic lights); large-scale communication equipment; key financial terminal systems; safety control equipment; etc.

Unless expressly designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not intended or authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems; surgical implantations; etc.), or may cause serious property damage (space system; undersea repeaters; nuclear power control systems; aircraft control systems; key plant systems; military equipment; etc.). Renesas Electronics disclaims any and all liability for any damages or losses incurred by you or any third parties arising from the use of any Renesas Electronics product that is inconsistent with any Renesas Electronics data sheet, user's manual or other Renesas Electronics document.

7. No semiconductor product is absolutely secure. Notwithstanding any security measures or features that may be implemented in Renesas Electronics hardware or software products, Renesas Electronics shall have absolutely no liability arising out of any vulnerability or security breach, including but not limited to any unauthorized access to or use of a Renesas Electronics product or a system that uses a Renesas Electronics product. RENESAS ELECTRONICS DOES NOT WARRANT OR GUARANTEE THAT RENESAS ELECTRONICS PRODUCTS, OR ANY SYSTEMS CREATED USING RENESAS ELECTRONICS PRODUCTS WILL BE INVULNERABLE OR FREE FROM CORRUPTION, ATTACK, VIRUSES, INTERFERENCE, HACKING, DATA LOSS OR THEFT, OR OTHER SECURITY INTRUSION ("Vulnerability Issues"). RENESAS ELECTRONICS DISCLAIMS ANY AND ALL RESPONSIBILITY OR LIABILITY ARISING FROM OR RELATED TO ANY VULNERABILITY ISSUES. FURTHERMORE, TO THE EXTENT PERMITTED BY APPLICABLE LAW, RENESAS ELECTRONICS DISCLAIMS ANY AND ALL WARRANTIES, EXPRESS OR IMPLIED, WITH RESPECT TO THIS DOCUMENT AND ANY RELATED OR ACCOMPANYING SOFTWARE OR HARDWARE, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY, OR FITNESS FOR A PARTICULAR PURPOSE.
8. When using Renesas Electronics products, refer to the latest product information (data sheets, user's manuals, application notes, "General Notes for Handling and Using Semiconductor Devices" in the reliability handbook, etc.), and ensure that usage conditions are within the ranges specified by Renesas Electronics with respect to maximum ratings, operating power supply voltage range, heat dissipation characteristics, installation, etc. Renesas Electronics disclaims any and all liability for any malfunctions, failure or accident arising out of the use of Renesas Electronics products outside of such specified ranges.
9. Although Renesas Electronics endeavors to improve the quality and reliability of Renesas Electronics products, semiconductor products have specific characteristics, such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Unless designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not subject to radiation resistance design. You are responsible for implementing safety measures to guard against the possibility of bodily injury, injury or damage caused by fire, and/or danger to the public in the event of a failure or malfunction of Renesas Electronics products, such as safety design for hardware and software, including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult and impractical, you are responsible for evaluating the safety of the final products or systems manufactured by you.
10. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. You are responsible for carefully and sufficiently investigating applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive, and using Renesas Electronics products in compliance with all these applicable laws and regulations. Renesas Electronics disclaims any and all liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
11. Renesas Electronics products and technologies shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You shall comply with any applicable export control laws and regulations promulgated and administered by the governments of any countries asserting jurisdiction over the parties or transactions.
12. It is the responsibility of the buyer or distributor of Renesas Electronics products, or any other party who distributes, disposes of, or otherwise sells or transfers the product to a third party, to notify such third party in advance of the contents and conditions set forth in this document.
13. This document shall not be reprinted, reproduced or duplicated in any form, in whole or in part, without prior written consent of Renesas Electronics.
14. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products.

(Note1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its directly or indirectly controlled subsidiaries.

(Note2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

(Rev. 1.01 Jul 22, 2025)

Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu,
Koto-ku, Tokyo 135-0061, Japan

www.renesas.com

Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.

Contact information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit:
www.renesas.com/contact/.

General Precautions in the Handling of Microprocessing Unit and Microcontroller Unit Products

The following usage notes are applicable to all Microprocessing unit and Microcontroller unit products from Renesas. For detailed usage notes on the products covered by this document, refer to the relevant sections of the document as well as any technical updates that have been issued for the products.

1. Precaution against Electrostatic Discharge (ESD)

A strong electrical field, when exposed to a CMOS device, can cause destruction of the gate oxide and ultimately degrade the device operation. Steps must be taken to stop the generation of static electricity as much as possible, and quickly dissipate it when it occurs. Environmental control must be adequate. When it is dry, a humidifier should be used. This is recommended to avoid using insulators that can easily build up static electricity. Semiconductor devices must be stored and transported in an anti-static container, static shielding bag or conductive material. All test and measurement tools including work benches and floors must be grounded. The operator must also be grounded using a wrist strap. Semiconductor devices must not be touched with bare hands. Similar precautions must be taken for printed circuit boards with mounted semiconductor devices.

2. Processing at power-on

The state of the product is undefined at the time when power is supplied. The states of internal circuits in the LSI are indeterminate and the states of register settings and pins are undefined at the time when power is supplied. In a finished product where the reset signal is applied to the external reset pin, the states of pins are not guaranteed from the time when power is supplied until the reset process is completed. In a similar way, the states of pins in a product that is reset by an on-chip power-on reset function are not guaranteed from the time when power is supplied until the power reaches the level at which resetting is specified.

3. Input of signal during power-off state

Do not input signals or an I/O pull-up power supply while the device is powered off. The current injection that results from input of such a signal or I/O pull-up power supply may cause malfunction and the abnormal current that passes in the device at this time may cause degradation of internal elements. Follow the guideline for input signal during power-off state as described in your product documentation.

4. Handling of unused pins

Handle unused pins in accordance with the directions given under handling of unused pins in the manual. The input pins of CMOS products are generally in the high-impedance state. In operation with an unused pin in the open-circuit state, extra electromagnetic noise is induced in the vicinity of the LSI, an associated shoot-through current flows internally, and malfunctions occur due to the false recognition of the pin state as an input signal become possible.

5. Clock signals

After applying a reset, only release the reset line after the operating clock signal becomes stable. When switching the clock signal during program execution, wait until the target clock signal is stabilized. When the clock signal is generated with an external resonator or from an external oscillator during a reset, ensure that the reset line is only released after full stabilization of the clock signal. Additionally, when switching to a clock signal produced with an external resonator or by an external oscillator while program execution is in progress, wait until the target clock signal is stable.

6. Voltage application waveform at input pin

Waveform distortion due to input noise or a reflected wave may cause malfunction. If the input of the CMOS device stays in the area between V_{IL} (Max.) and V_{IH} (Min.) due to noise, for example, the device may malfunction. Take care to prevent chattering noise from entering the device when the input level is fixed, and also in the transition period when the input level passes through the area between V_{IL} (Max.) and V_{IH} (Min.).

7. Prohibition of access to reserved addresses

Access to reserved addresses is prohibited. The reserved addresses are provided for possible future expansion of functions. Do not access these addresses as the correct operation of the LSI is not guaranteed.

8. Differences between products

Before changing from one product to another, for example to a product with a different part number, confirm that the change will not lead to problems. The characteristics of a microprocessing unit or microcontroller unit products in the same group but having a different part number might differ in terms of internal memory capacity, layout pattern, and other factors, which can affect the ranges of electrical characteristics, such as characteristic values, operating margins, immunity to noise, and amount of radiated noise. When changing to a product with a different part number, implement a system-evaluation test for the given product.

How to Use This Manual

1. Purpose and Target Readers

This manual is designed to provide the user with an understanding of the hardware functions and electrical characteristics of the MPU. It is intended for users designing application systems incorporating the MPU. A basic knowledge of electric circuits, logical circuits, and MPUs is necessary in order to use this manual.

The manual comprises an overview of the product; descriptions of the CPU, system control functions, peripheral functions, and electrical characteristics; and usage notes.

Particular attention should be paid to the precautionary notes when using the manual. These notes occur within the body of the text, at the end of each section, and in the Usage Notes section.

The revision history summarizes the locations of revisions and additions. It does not list all revisions. Refer to the text of the manual for details.

The following documents apply to the RZ/V2N Group and RZ/G3E Group. Make sure to refer to the latest versions of these documents. The newest versions of the documents listed may be obtained from the Renesas Electronics Web site.

Document Type	Description	Document Title	Document No.
User's manual for Hardware	Hardware specifications (pin assignments, memory maps, peripheral function specifications, electrical characteristics, timing charts) and operation description Note: Refer to the application notes for details on using peripheral functions.	RZ/V2N Group User's Manual: Hardware	---
		RZ/G3E Group User's Manual: Hardware	---
User's manual for Software	Description of USB Host Linux interface Specification	Linux Interface Specification Device Driver USB3.2 Host	This user's manual
Application Note	Information on using peripheral functions and application examples Sample programs Information on writing programs in assembly language and C	Available from Renesas Electronics Web site.	
Renesas Technical Update	Product specifications, updates on documents, etc.		

2. Notation of Numbers and Symbols

3. Register Notation

4. List of Abbreviations and Acronyms

Abbreviation	Description
BSP	Board Support Package
CPRM	Content Protection for Recordable Media
DMA	Direct Memory Access
DMAC	DMA Controller
EHCI	Enhanced Host Controller Interface
GPL	GNU General Public License
LGPL	GNU Lesser General Public License
MTD	Memory Technology Device
NCQ	Native Command Queuing
OHCI	Open Host Controller Interface
OSS	Open Source Software
USB	Universal Serial Bus
VLP	Verified Linux Package
xHCI	Extensible Host Controller Interface

Table of Contents

1. Overview.....	1
1.1 Overview	1
1.2 Function	1
1.3 Connected Port	1
1.4 Reference	2
1.4.1 Standard.....	2
1.4.2 Related Documents.....	2
1.5 Restrictions	2
2. Terminology.....	3
3. Operating Environment.....	4
3.1 Hardware Environment	4
3.2 Module Configuration.....	5
3.3 State Transition Diagram	6
4. External Interface.....	7
5. Integration.....	8
5.1 Directory Configuration	8
5.1.1 Device tree definition.....	8
5.2 Integration Procedure	10
5.2.1 Kernel Configuration	10
5.3 Option Setting	12
5.3.1 Module Parameters.....	12
5.3.2 Kernel Parameters	12

1. Overview

1.1 Overview

This manual explains the driver module (this module) that controls the USB 3.2 Host controller on RZ/V2N Group and RZ/G3E Group.

- Support for super-speed plus (10 Gbps), super-speed (5 Gbps), high-speed (480 Mbps), full-speed (12Mbps), and low-speed (1.5 Mbps) transfer.
- Support for all transfer types: isochronous, interrupt, control, and bulk.
- Support for isochronous and interrupt high-band transfer.
- Compliant with the eXtensible Host Controller Interface(xHCI) Specification for USB.

1.2 Function

This module controls the USB 3.2 Host controller on RZ/V2N, RZ/G3E transmits/receives data to/from the USB device.

The function of this module is based on eXtensible Host Controller Interface (xHCI) of standard Linux.

- USB memory device support
- USB keyboard device support
- USB mouse device support

1.3 Connected Port

Connected USB 3.2 ports on the RZ/V2N, RZ/G3E boards are described in below tables.

Table 1-1 Connected Port (RZ/V2N)

Port No.	Standard	Connector	Content
0	USB3.2 Host	USB1B-1A_HOST	Type A connector

Note: All the information on the above table is used for RZ/V2N.

Table 1-2 Connected Port (RZ/G3E)

Port No.	Standard	Connector	Content
0	USB3.2 Host	USB2_HOST	Type A connector

Note: All the information on the above table is used for RZ/G3E.

1.4 Reference

1.4.1 Standard

Table 1-3 Standard (RZ/V2N, RZ/G3E)

Reference No.	Issue	Title	Edition	Date
-	USB Implementers Forum, Inc	Universal Serial Bus 3.0 Specification	Rev.1.0	Jun. 6, 2011

1.4.2 Related Documents

There is no document related to this module.

1.5 Restrictions

There is no restriction in this module.

2. Terminology

The following table shows the terminology related to this module.

Table 2-1 Terminology

Terms	Explanation
USB	Universal Serial Bus
HCD	Host Controller Driver
xHCI	eXtensible Host Controller Interface

3. Operating Environment

3.1 Hardware Environment

The following table shows the hardware needed to use this module.

Table 3-1 Hardware specification

Name	Product number
RZ/V2N Evaluation Kit	RTK0EF0186C03000BJ
RZ/G3E Evaluation Board Kit	RTK9947E57S01000BE

3.2 Module Configuration




Figure 3-1 Modules Configuration (RZ/V2N, RZ/G3E)

Note: All the information in the above diagram is used for RZ/V2N and RZ/G3E

Board	Port 0
RZ/V2N	USB1B-1A_HOST
RZ/G3E	USB2_HOST

3.3 State Transition Diagram

The following table shows the state transition of this module.




Figure 3-2 State Transition Diagram (RZ/V2N, RZ/G3E)

4. External Interface

Detailed explanation is skipped because the external interface of this module is based on Linux.

Device node of this module is shown below.

Table 4-1 Device Node (RZ/V2N, RZ/G3E)

Device	Channel	Device node	Major number	Minor number
Keyboard	0	/dev/input/eventX *	13	64 - 66
Mouse	0	/dev/input/mouseX1	13	32 - 33
USB memory	0	/dev/sdX1	8	0 - 1

Note: * The numerical value may differ according to the system. (ex, /dev/input/event0).

5. Integration

5.1 Directory Configuration

The directory configuration is shown below.




Figure 5-1 Directory Configuration (RZ/V2N, RZ/G3E)

5.1.1 Device tree definition

Below figure lists the necessary properties to support USB 3.2 host in RZ/V2N Evaluation Board Kit.

```

usb3_phy0: usb-phy@15870000 {
    compatible = "renesas,usb3-phy-r9a09g056",
                 "renesas,rz-usb3-phy";
    reg = <0 0x15870000 0 0x10000>;
    clocks = <&cpg CPG_MOD 0xb0>;
    power-domains = <&cpg>;
    resets = <&cpg 0xaa>;
    #phy-cells = <0>;
    status = "disabled";
};
xhci0: usb@15850000 {
    compatible = "renesas,rzv2n-xhci";
    reg = <0 0x15850000 0 0x10000>;
    interrupts = <GIC_SPI 759 IRQ_TYPE_LEVEL_HIGH>;
    clocks = <&cpg CPG_MOD 0xaf>,
            <&cpg CPG_MOD 0xb0>;
    clock-names = "reg", "usbtst";
    power-domains = <&cpg>;
    resets = <&cpg 0xaa>;
    phys = <&usb3_phy0>;
    phy-names = "usb0";
    status = "disabled";
}
  
```

Figure 5-2: Enable USB3.2 host device nodes (r9a09g056.dtsi)

Note: All the information in above device tree is used for RZ/V2N.

Below figure lists the necessary properties to support USB 3.2 host in RZ/G3E Evaluation Board Kit.

```
usb3_phy: usb-phy@15870000 {
    compatible = "renesas,usb3-phy-r9a09g047",
                "renesas,rz-usb3-phy";
    reg = <0 0x15870000 0 0x10000>;
    clocks = <&cpg CPG_MOD 0xb0>;
    power-domains = <&cpg>;
    resets = <&cpg 0xaa>;
    #phy-cells = <0>;
    status = "disabled";
};
xhci: usb@15850000 {
    compatible = "renesas,rzg3e-xhci";
    reg = <0 0x15850000 0 0x10000>;
    interrupts = <GIC_SPI 759 IRQ_TYPE_LEVEL_HIGH>;
    clocks = <&cpg CPG_MOD 0xaf>;
    clock-names = "reg";
    power-domains = <&cpg>;
    resets = <&cpg 0xaa>;
    phys = <&usb3_phy>;
    phy-names = "usb";
    status = "disabled";
};
```

Figure 5-3: Enable USB3.2 host device nodes (r9a09g047.dtsi)

Note: All the information in above device tree is used for RZ/G3E.

Below figure enables the necessary properties to support USB 3.2 host in RZ/V2N Evaluation Board Kit.

```
&xhci0 {
    pinctrl-0 = <&usb30_pins>;
    pinctrl-names = "default";

    memory-region = <&global_cma>;
    status = "okay";
};
&usb3_phy {
    status = "okay";
};
```

Figure 5-4: Enable USB 3.2 Host (r9a09g056n44-evk.dts)

Below figure enables the necessary properties to support USB 3.2 host in RZ/G3E Evaluation Board Kit.

```
&xhci {
    pinctrl-0 = <&usb3_pins>;
    pinctrl-names = "default";

    memory-region = <&global_cma>;
    status = "okay";
};

&usb3_phy {
    status = "okay";
};
```

Figure 5-5: Enable USB 3.2 Host (rzg3e-smarc.dtsi)

5.2 Integration Procedure

5.2.1 Kernel Configuration

To enable the functions of this module, make the following setting with Kernel Configuration.

```
Device Drivers --->
[*] USB support ---->
    <*> Support for Host-side USB
    ...
        *** USB Host Controller Drivers ***
    <*> xHCI HCD (USB 3.0) support
    <*> Generic xHCI driver for a platform device
    -* xHCI support for Renesas RZ/V2H SoC
    ...
Device Drivers --->
[*] PHY Subsystem ---->
    <*> Renesas R-Car generation 3 USB 3.0 PHY driver
```

Figure 5-6 Kernel configuration for this module (RZ/V2N, RZ/G3E)

The following shows an example of integration of standard USB class drivers.

```
Device Drivers --->
  [*] SCSI device support ---->
    *- SCSI device support
    ...
    [] legacy /proc/scsi/ support
      *** SCSI support type (disk, tape, CD-ROM) ***
    <*> SCSI disk support

Device Drivers --->
  [*] USB support ---->
    *** NOTE: USB_STORAGE depends on SCSI but BLK_DEV_SD may ***
    *** also be needed; see USB_STORAGE Help for more info ***
    <*> USB Mass Storage support

Device Drivers --->
  Input device support ---->
    <*> Event interface

Device Drivers --->
  HID support ---->
    <*> Generic HID driver
      USB HID support ---->
        <*> USB HID transport layer
```

Figure 5-7: Kernel configuration for standard USB class drivers (RZ/V2N, RZ/G3E)

5.3 Option Setting

5.3.1 Module Parameters

There are no module parameters.

5.3.2 Kernel Parameters

There are no kernel parameters.

Revision History	Linux Interface Specification Device Driver USB3.2 Host User's Manual: Software
------------------	--

Rev.	Date	Description	
		Page	Summary
1.00	Jun. 30, 2025	—	First Edition issued
1.01	Jul. 22, 2025	1-3	Add RZ/G3E overview, name board, product number and connected port.
		5	Update Modules Configuration for RZ/G3E
		6-7, 11	Update information about RZ/G3E
		9 – 10	Update Figure 5-2: Add usb3_phy0 device node Add figure 5-3: Add USB3.2 host device nodes. Add figure 5-5: Enable USB 3.2 Host for RZ/G3E.

Linux Interface Specification Device Driver USB3.2 Host
User's Manual: Software

Publication Date: Rev. 1.01 Jul 22, 2025

Published by: Renesas Electronics Corporation

RZ/V2N Group and RZ/G3E Group



Renesas Electronics Corporation