

### Contents

1. Target Devices .....	2
2. User's Manuals .....	3
3. Uninstallation .....	4
4. Improvements and Changes .....	5
5. Points for Caution .....	12
6. Restrictions .....	22
Revision Record .....	27

## 1. Target Devices

The target devices supported by the CS+ are listed on the Website.

Please see this URL.

CS+ Product Page

<https://www.renesas.com/cs+>

## 2. User's Manuals

Please read the following user's manuals along with this document.

Manual Name	Document Number
CS+ V8.14.00 Installer	R20UT5672EJ0100
CS+ V8.13.00 Editor	R20UT5561EJ0100
CS+ V8.15.00 Python Console	R20UT5746EJ0100
CS+ V8.14.00 Updater	R20UT5568EJ0100
CS+ V8.14.00 Message	R20UT5669EJ0100
CS+ V8.15.00 Project Operation	R20UT5743EJ0100
CS+ V8.11.00 Analysis Tool	R20UT5394EJ0100
CS+ V8.15.00 RH850 Debug Tool	R20UT5745EJ0100
CS+ V8.15.00 RX Debug Tool	R20UT5759EJ0100
CS+ V8.15.00 RL78 Debug Tool	R20UT5744EJ0100
CS+ User's Manual: CC-RH Build Tool Operation	R20UT3283EJ0113
CS+ User's Manual: CC-RL Build Tool Operation	R20UT3284EJ0114
CS+ User's Manual: CC-RX Build Tool Operation	R20UT3478EJ0112
CS+ V8.15.00 GHS CCRH850 Build Tool Operation	R20UT5742EJ0100

\* GHS: Green Hills Software, LLC

### 3. Uninstallation

There are two ways to uninstall this product.

- Use the integrated uninstaller from Renesas (uninstalls all CS+ components)
- Use the Windows uninstaller (only uninstalls this product)

To use the Windows uninstaller, select [CS+ for CC] from [Apps & features] from [Settings] of Windows or [Programs and Features] of the control panel.

## 4. Improvements and Changes

This chapter describes changes from V8.14.00 to V8.15.00.

### 4.1 Improvements and changes to CS+

#### 4.1.1 Enhanced support for Renesas compilers [RL78]

Support for the following compiler have been added.

- C Compiler Package for RL78 Family CC-RL V1.16.00

For details of updates and points for caution on the compiler, refer to the release note for the compiler.

#### 4.1.2 Enhanced support for GHS compilers [RH850]

Support for the following version of the RH850 compiler from GHS has been added.

- 2025.1.4

## 4.2 Additions and improvements to the build tool

### 4.2.1 Improvement to updating the dependencies during the building of FAA assembly source files [RL78]

CS+ now has functionality for updating dependency information on FAA assembly source files.

When the following conditions are satisfied, dependency information on FAA assembly source files will be updated.

- The version of the FAA/GREEN\_DSP structured assembler is V1.06.00 or later.
- [Use compiler for updating dependencies to increase accuracy over speed of analysis when the functionality is available] is selected for [General – Build] in the [Option] dialog box.

### 4.2.2 Improvement to updating the dependencies during the building of SMS assembly source files [RL78]

CS+ now has functionality for updating dependency information on SMS assembly source files.

When the following conditions are satisfied, dependency information on SMS assembly source files will be updated.

- The version of the SMS assembler is V1.01.00 or later.
- [Use compiler for updating dependencies to increase accuracy over speed of analysis when the functionality is available] is selected for [General – Build] in the [Option] dialog box.

### 4.2.3 Improvement to building when a project is reused or converted [RX]

In CS+ for CC V8.14.00, the [Instruction-set architecture] and [Microcontroller type] properties have been changed so that user specification is not possible (the properties are read-only).

As a result of the change, the following build error would occur for projects that matched all specific conditions, but the phenomenon has now been rectified.

F0553103:Option '-isa=rxv1 -nofpu' is not appropriate

[Phenomenon]

The build error occurs when all of the following conditions are met :

Version: CS+ for CC V8.14.00

Conditions:

- The project was created using CS+ for CC V8.13.00 or an earlier version.
- The [Instruction-set architecture] property was modified from the expected value for the device.
- The [Microcontroller type] property under the [CPU] category on the [Common Options] tabbed page set to [RX200 or RX100 series (-cpu=rx200)].
- The [Uses single-precision floating-point operation instructions] property under the [CPU] category on the [Common Options] tabbed page set to [Depends on the Microcontroller type option].
- The [Build simultaneously] property under the [Build Method] category on the [Common Options] tabbed page is set to [Yes].
- The project contains an assembly source.

#### 4.2.4 Improvement when a project for GHS CCRH850 is reused [RH850]

When a project for GHS CCRH850 is reused, nothing would be displayed for properties of the build tool. However, the phenomenon has now been rectified so that the properties are displayed.

[Phenomenon]

Version: CS+ for CC V4.01.00 - CS+ for CC V8.14.00

Steps which produce the phenomenon:

1. Create a project using [Empty Application (GHS CCRH850)]. (This will be referred to as Project\_A.)
2. Then, create a new project using [Use Existing GHS Project File (GHS CCRH850)]. (This will be referred to as Project\_B.)

During this step, check the [Pass the file composition of an existing project to the new project] check box and specify the full path to Project\_A as the source.

-> After creating Project\_B, when you select "GHS CCRH850 (Build Tool)" in the project tree, nothing is displayed in the property panel.

This also occurs if the kind of projects of Project\_A and Project\_B are swapped.

#### 4.2.5 Improvement to building in specific versions of the assembler [RL78][RX][RH850]

When the following setting in [General - Build] in the [Option] dialog box is enabled (it is selected by default) and a project is built with any of the versions of the compiler package listed below, the phenomenon of the assembler always being executed even if the assembly source file has not been edited would arise.

The setting: [Use compiler for updating dependencies to increase accuracy over speed of analysis when the functionality is available]

Versions where the phenomenon occurs:

- Versions of CS+: CS+ for CC V8.02.00 - CS+ for CC V8.14.00
- Versions of compiler packages:
  - CC-RX V2.00.00 - V2.03.00
  - CC-RL V1.00.00 - V1.02.00
  - CC-RH V1.00.00 - V1.05.00

However, the phenomenon has been rectified so that the assembler is only executed when the assembly source file or include file is edited.

## 4.3 Additions and improvements to the debug tool

The abbreviations listed below collectively denote the corresponding tools in this section.

OCD (serial):

Serial or FINE interface connection for the E1 emulator, E20 emulator, E2 emulator, and E2 emulator Lite

OCD (JTAG):

JTAG interface connection for the E1 emulator, E20 emulator, E2 emulator, and E2 emulator Lite

OCD (LPD):

LPD connection for the E1 emulator, E20 emulator, and E2 emulator

### 4.3.1 Change to the default value for [Initialize unused space during flash programming] [RL78]

The default value of the [Connect Settings] tab > [Flash] category > [Initialize unused space during flash programming] property has been changed from [No] to [Yes].

### 4.3.2 Support for simulation of flash memory with the RL78 simulator for peripheral modules [RL78]

Applies to: The simulators for RL78/G22, RL78/G23, RL78/G24, and RL78/L23 devices

The target simulator for peripheral modules now supports self-programming, boot swapping, and bank programming (only for RL78/L23 devices) of flash memory.

The following properties have been added to the RL78/L23 simulator.

- [Connect Settings] tab > [Flash] category > [Change BTBLS to use bank swapping when connecting] property
- [Connect Settings] tab > [Flash] category > [Change boot cluster size for BTBLS on connection [KB]] property

### 4.3.3 Improvement to the condition for displaying the [Select I/O modules which details are displayed] property [RH850]

The following property was formerly displayed only when the selected microcontroller requires the settings. However, the property is now always displayed when an RH850 device is selected.

- [Debug Tool Settings] tab > [Memory] category > [Select I/O modules which details are displayed] property

If you are using a project created with CS+ V8.14.00 or an earlier version and selected the I/O module for which details are displayed in [I/O modules], change the [Select I/O modules which details are displayed] property to [Yes].

### 4.3.4 Extending the range of products for which the simulation of peripheral modules and current drawn is supported [RL78]

Applies to: The simulators for RL78/L23 devices

Support for the simulation of peripheral modules and current drawn has been extended to further products. This enables the simulation of peripheral modules and current drawn for those products in only a virtual environment on a PC, i.e. without having to connect CS+ to the actual MCU (on a board).

The following MCU is newly supported for the simulation of peripheral modules and current drawn.

- RL78/L23\*

Note: Simulation of peripheral modules for all RL78/L23 products is now enabled in this version.

**4.3.5 Addition of types of components supported on the [Virtual Board] panel [RL78]**

**Applies to:** The simulators for RL78/G10, RL78/G11, RL78/G12, RL78/G13, RL78/G13A, RL78/G14, RL78/L12, RL78/G1F, RL78/G23, RL78/G15, RL78/G22, RL78/G16, RL78/G24 and RL78/L23 devices

Support for the following types of component has been added to the [Virtual Board] panel.

MIDI Device, EEPROM

## 4.4 Improvement to the update manager

### 4.4.1 Improvement to the update functions of the update manager

The update manager has now been improved so that it can update its own functionality.

## 4.5 Improvement to the I/O header file generation tool

### 4.5.1 Improvement to the header files or include files generated by the I/O header file generation tool [RL78]

The license which is applied to header files or include files generated by this tool has now been changed to the BSD-3-Clause.

For details on the license, refer to the file below.

CS+ *install folder\CC\Utilities\IOHeaderGenerator\license.txt*

## 5. Points for Caution

This section describes points for caution regarding CS+.

### 5.1 Points for caution regarding CS+ (general)

#### 5.1.1 File names

The following rules apply to folder and file names.

Types of Folder and File Names	Rules
Paths (folder and file names)	<ul style="list-style-type: none"> <li>● Naming folder and file names complies with rules for naming files in Windows.</li> <li>➤ Do not use folder and file names which cannot be created in Windows Explorer. The following characters are not usable. ＼, /, :, *, ?, ", &lt;, &gt;,  </li> <li>➤ English upper-case (A – Z) and lower-case (a – z) characters are not distinguished from each other.</li> <li>● Up to 259 characters can be used.</li> <li>● The following character cannot be used. <ul style="list-style-type: none"> <li>➤ Characters in system-dependent character codes</li> <li>➤ ^ [CC-RH/CC-RL]</li> </ul> </li> <li>● Network path names cannot be used. Assign such names to drives.</li> </ul>
Build mode names (names of folders output by a linker)	<ul style="list-style-type: none"> <li>● Also refer to the notes on paths (folder and file names) above.</li> <li>● The following characters are not usable. <ul style="list-style-type: none"> <li>➤ , = ;</li> <li>➤ - [Only the first character for CC-RX]</li> </ul> </li> </ul>
Source file names Load module names Project names (names of files output by a linker)	<ul style="list-style-type: none"> <li>● Also refer to the notes on paths (folder and file names) above.</li> <li>● Only the characters a to z, A to Z, 0 to 9, . (period), _ (underscore), +, and - are usable. However, a period (.) cannot be used at the start or end of a file name. Plus (+) and minus (-) cannot be used at the start of a file name.</li> <li>● Do not use source files with the same names. If such files exist along different paths, the names cannot be distinguished.</li> </ul>

#### 5.1.2 Panel display

If your hardware environment does not meet the recommended specifications for CS+, the [Property] panel may appear small and have scrambled contents.

If this happens, move the [Property] panel outside the split panel area.

- Enable [Dockable], and make it a docking panel
- Enable [Floating], and make it a floating panel

### 5.1.3 [Editor] panel

- When a label is selected and the [Jump to Function or Variable] feature is used from the context menu, execution does not jump to the label.
- The following notes apply to the editor, when source files with the same name but from different folders are registered with a main project and a sub project, and load modules from both the main project and sub project are downloaded.
  - The address of the main project is displayed on the file.
  - At jumping to a source file from disassembled code, the file registered with the main project is opened.
  - If the file is opened from either project, only one file will be opened.
- On Windows 10 and Windows 11, the display may become unclear due to anti-aliasing.
- When saving a file in the [Save As] dialog box, the extension listed at the top of the [Save as type] drop-down list is automatically added unless another extension is specified. Note however, that an extension is not added when a file name is input with an extension that is selected in the [Save as type] drop-down list or with an extension that is registered with Windows. When an automatically added extension is not as expected, modify the name of the file by using, for example, Explorer.
- When the floating [Editor] panel is displayed on Windows 11, snap layouts are not displayed even if the mouse cursor is hovered over the maximize button.  
Workaround: Enter the Windows key + Z.
- Immediately after colors have been customized with [General – Font and Color] in the Option dialog box, the character strings for the search are not highlighted. To highlight these strings, restart CS+.

### 5.1.4 Creating new projects

Applies to: RX

If a new project is created by selecting [Empty Application[CC-RX]] under the environment for the RX, building the project may lead to the following errors.

```
** L2132 (E) Cannot find "D" specified in option "rom"
** L2132 (E) Cannot find "D_1" specified in option "rom"
** L2132 (E) Cannot find "D_2" specified in option "rom"
```

If you encounter these errors, change the setting of [ROM to RAM mapped section] on the [Link Options] sheet in CS+.

### 5.1.5 Tutorials

The Code Generator Plug-in, Pin Configurator Plug-in and Program Analyzer Plug-in are used in tutorials.

Enable them through the [Plug-in Manager] dialog box.

### 5.1.6 Starting multiple instances of CS+

Two or more instances of CS+ can be started on the same host machine, but if you do so, take note of the points listed below.

- When two or more instances of CS+ are started, the most recent information to have been written is saved in the information file for each user's own PC.
- When two or more instances of CS+ are started, the most recent information to have been written is saved in the information file for the stack analysis tools (including CallWalker).
- When the same project file is used in two or more instances of CS+, the most recent information to have been written is saved.
- When the same project file is used in two or more instances of CS+, do not attempt building from more than one instance at the same time since the names of the output files will be identical.

### 5.1.7 Loading projects by using earlier versions of CS+

If the version of CS+ being used to load a project is earlier than the CS+ version with which the project was created, some settings may be cleared since the earlier versions of CS+ do not recognize them.

### 5.1.8 Dual-bank function of the code flash memory

**Applies to:** RX26T, RX65N/RX651-2M, RX65W-A, RX671, RX66N, RX72N and RX72M group

Products of the RX26T group with 512 KB of ROM, RX65N and RX651 groups with 2 or 1.5 MB of ROM, RX65W-A, RX671, RX66N, RX72N and RX72M support the dual-bank function of the code flash memory. In CS+, you can select the linear or dual mode during the process of setting up a project.

In use of dual mode, select the type name with “\_DUAL”.

### 5.1.9 Smart Manual

**Applies to:** RX, RL78

When the Smart Manual does not support the target MCU of an open project, the user's manuals are not displayed.

### 5.1.10 Smart Manual for CS+ for CC V8.09.00 or an earlier version

**Applies to:** RL78, RX

The form of distribution of the database for the Smart Manual has been changed from April 2023.

Versions of manuals that were updated or disclosed after April 2023 cannot be automatically opened in the Smart Manual panel for CS+ for CC V8.09.00 or an earlier version.

Consider updating of the version of CS+ to CS+ for CC V8.10.00 or later.

### 5.1.11 CS+ Partner OS Aware Debugging Plug-in

**Applies to:** RL78, RX

When CS+ is started with the CS+ Partner OS Aware Debugging Plug-in enabled and by using CubeSuite+.exe (without the Main window), the error message “(0202002) Opening a project failed.” is returned.

This can be avoided in either of the following ways.

- Start CS+ by specifying an option to prevent reading of the CS+ Partner OS Aware Debugging Plug-in for CubeSuite+.exe.  
Example: CubeSuite+.exe /np PartnerOS ...
- Turn off the CS+ Partner OS Aware Debugging Plug-in before starting CS+ with CubeSuite+.exe (without the Main window).

How to turn off the plug-in:

Start CS+ (with the Main window) or CubeSuite+ (CubeSuiteW+.exe).

Select [Plug-in Setting...] from the [Tool] menu to display the [Plug-in Manager] dialog box.

Deselect the [CS+ Partner OS Aware Debugging Plug-in] checkbox.

### 5.1.12 RX72M

When creating a new RX72M project, there are differences between the register definition contents of iodefine.h and the contents of the RX72M User's Manual.

Applicable iodefine.h file version is V1.00A and earlier.

1. Error : unsigned short ACKCMDER:1;  
Correct : unsigned short ACKCMDERR:1;
2. Error : unsigned long PSADR:19;  
Correct : unsigned long PSADR:17;

### 5.1.13 Displaying Find and Replace dialog box

The position of the Find and Replace dialog box is remembered and restored. In a multi-display environment, for example, in case that the sub display is temporarily OFF, the Find and Replace dialog box may not appear due to being off the screen.

In the case, it is possible to move to the visible position in the following way:

1. Immediately after entering Ctrl+F, in other word, with the focus on the Find and Replace dialog box, enter the Alt+Spacebar. The control menu will appear, enter the M key to select [Move].
2. Enter the arrow keys in that state, or move the mouse cursor to display the dialog.

### 5.1.14 Editing and analyzing C++ source files [RL78]

In a CC-RL project, the following functions regarding a C++ source file cannot be used.

- The smart edit function in the Editor panel
- Functions of an analysis tool
  - Function List panel
  - Variable List panel
  - Analysis Chart panel (except for the [Variable Value Changing Chart] tabbed page)
  - Call Graph panel
  - Class/Member panel

Regarding support for C++ by the CC-RL compiler, refer to the help system, User's Manual: Compiler, or the release notes for the compiler.

## 5.2 Points for caution regarding build tools

### 5.2.1 Projects to which C++ source files have been added [RL78]

If a project for CC-RL has been created with CS+ V8.09.00 or a later version, it cannot be opened with CS+ V8.08.00 or an earlier version if any C++ source files have been registered with the project.

This is because CS+ V8.08.00 and earlier versions do not support C++ source files.

### 5.2.2 Changing the microcontroller

When you change the microcontroller, some options may not be correctly changed because of the difference of specifications between the microcontrollers before and after the change.

For the changed options, messages will be output to the Output panel in the following format.

[Name of a property] <Setting before the change> -> <Setting after the change>

A source file for starting up CS+ is not updated to take account of the change to the microcontroller.

When you have changed the microcontroller, check the specifications of the microcontroller after the change, modify the source file for starting up CS+, and re-set the options.

### 5.2.3 Creating or converting a project from an existing project [RX]

When a project is created by specifying [Pass the file composition of an existing project to the new project] or a project of the e<sup>2</sup> studio or High-performance Embedded Workshop is to be converted into one for CS+, the E0291010 message may appear several times. Click on the [OK] button for the message every time it appears.

If this message appears, confirm that the [Using compiler package version] property ([Common Options] tabbed page > [Version Select] category) has been correctly set after the project was created or converted from an existing project.

## 5.3 Points for caution regarding design tools

### 5.3.1 Saving projects

If you save a project that has sub-projects while the [Device Top View] or [Device Pin List] panel is open, then the device top view and device pin list of the main project will always appear.

## 5.4 Points for caution regarding debugging tools

The abbreviations listed below collectively denote the corresponding tools in this section.

OCD (serial):

Serial or FINE interface connection for the E1 emulator, E20 emulator, E2 emulator, and E2 emulator Lite

OCD (JTAG):

JTAG interface connection for the E1 emulator, E20 emulator, E2 emulator, and E2 emulator Lite

OCD (LPD):

LPD connection for the E1 emulator, E20 emulator, and E2 emulator

### 5.4.1 Adding sub-projects

**Applies to:** Common to all debugging tools and devices

If you add a sub-project while a debugging tool is connected, downloading and so on may fail. Only add sub-projects while the debugging tool is disconnected.

### 5.4.2 Assigning unions to registers

**Applies to:** All debugging tools for RX

When a union is assigned to a register, it is assumed that the members of the union are assigned to the lower-order bytes of the register. For this reason, the values of the members will be incorrect when displayed as big endian.

### 5.4.3 Functions with the same name and char-type parameters

**Applies to:** All debugging tools for RX

When three functions with char-type parameters are defined as shown below, the address of "Func(signed char)" will not be displayed (i.e. the address of "Func(char)" will be displayed instead).

```
void Func(char);  
void Func(signed char);  
void Func(unsigned char);
```

### 5.4.4 Changing the priority section among overlaid sections

**Applies to:** All debugging tools for RX

Changing the priority section among overlaid sections is not immediately reflected in debugger operations. To update the display of addresses in the editor, for example, you need to close the file and open it again. To update the display of variables in the [Watch] panel, execute a single step of the program.

### 5.4.5 Linkage options of CC-RX

**Applies to:** All debugging tools for RX

CC-RX does not support the '-sdebug' linkage option.

Please set [Outputs debugging information] in the [output] category of the [Link Options] tabbed page to '-debug'.

#### 5.4.6 Breakpoints in for statements or inline-expanded functions

**Applies to:** All debugging tools for all devices

If a line of C source code includes any of the functions or statements listed below, the instruction is placed at two or more addresses. However, the editor panel shows only one of the addresses.

In cases where a breakpoint is set on this line, the program stops only when the instruction at the address being displayed on the editor panel is executed.

1. Inline-expanded function (\*)
  2. Template function
  3. First line of a for or do-while statement
- \* Includes those inline-expanded by optimization

#### 5.4.7 Notice of the project of dual mode

**Applies to:** All debugging tools for RX65N-2M, RX651-2M, RX671, RX66N, RX72N, RX72M group

Group	Size of ROM
<b>RX65N-2M, RX651-2MB, RX671</b>	Less than 1.5MB of ROM
<b>RX66N, RX72N, RX72M</b>	Less than 2.0MB of ROM

In case of a project of a dual mode of a device with above ROM size, a gap exists during the address of the ROM in bank 0 and bank 1.

But data in a gap exists in the following function.

- Memory panel
- Watch panel
- Disassemble panel

[E1/E20/E2/E2Lite]

Read result is 0x00, Write is ignored.

[Simulator]

Read and Write operate correctly.

#### 5.4.8 Notice regarding the IE850A

**Applies to:** IE850A for RH850

Values larger than [512K] can be specified for the [Trace memory size [frames]] property. If such values are specified, however, only the latest 512 K frames of trace data will be used in the display of the [Trace] panel and in the Python console.

#### 5.4.9 Notice regarding the RL78/G1M, RL78/G1N

**Applies to:** OCD (serial) for RL78/G1M, RL78/G1N

The following properties cannot be used with RL78/G1M and RL78/G1N.

Connect Setting - Connection with Target Board - Low voltage OCD board

#### 5.4.10 Simulation of peripheral modules

**Applies to:** The simulators for RL78/G10, RL78/G11, RL78/G12, RL78/G13, RL78/G13A, RL78/G14, RL78/L12, RL78/G1F, RL78/G23, RL78/G15, RL78/G22, RL78/G16, RL78/G24 and RL78/L23 devices

Operation of CS+ may be incorrect if the user program or a debugging operation makes settings of the SFR which are prohibited in the user's manual for the target device.

#### 5.4.11 Point for caution on time measurement by the simulator when the device is in standby mode

**Applies to:** The simulators for RL78 and RH850

When the program is on standby (in halt, stop, or snooze mode for an RL78 device and in halt mode for an RH850 device), time measurement by the following facilities does not operate correctly.

(1) Run-break timer facility (for RL78 simulator and RH850 simulator)

The run-break time is not correctly measured in the following cases.

- A forced break occurred in standby mode.
- A program is run following standby mode (run after a forced break).

(2) The Python function debugger.Interrupt.SetTimer (only for the RH850 simulator)

Even if the break time specified with debugger.Interrupt.SetTimer is matched on standby (in halt mode), the break does not occur until the program is released from standby.

This also applies in cases when the break time was specified with debugger.XRunBreak.Set since it is based on the same functionality.

#### 5.4.12 Notice regarding the [Virtual Board] panel

**Applies to:** The simulators for RL78/G10, RL78/G11, RL78/G12, RL78/G13, RL78/G13A, RL78/G14, RL78/L12, RL78/G1F, RL78/G23, RL78/G15, RL78/G22, RL78/G16 and RL78/G24 devices

When a project that meets all the following conditions is loaded in CS+ for CC V8.11.00 or later and the [Virtual Board] panel is activated, it is read with the virtual components and the simulator disconnected.

- A project created with CS+ for CC V8.09.00 or earlier.
- A project which the microcontroller has been changed.
- A project which the [Virtual Board] panel has been activated.

## 5.5 Points for caution regarding analysis tools

### 5.5.1 [Variable Value Changing Chart] tabbed page of the Analysis Chart panel

If a project is opened and saved in CS+ V8.09.00 or an earlier version, the settings for channel 17 and subsequent channels on the [Variable Value Changing Chart] tabbed page of the Analysis Chart panel will be lost.

## 6. Restrictions

This section describes restrictions on CS+.

### 6.1 Restrictions imposed by debugging tools

The abbreviations listed below collectively denote the corresponding tools in this section.

OCD (serial):

Serial or FINE interface connection for the E1 emulator, E20 emulator, E2 emulator, and E2 emulator Lite

OCD (JTAG):

JTAG interface connection for the E1 emulator, E20 emulator, E2 emulator, and E2 emulator Lite

OCD (LPD):

LPD connection for the E1 emulator, E20 emulator, and E2 emulator

#### 6.1.1 List of restrictions imposed by debugging tools

No.	Target tool	Target device	Description	Remarks
1	All debugging tools	RL78, RX, RH850	Division of load modules	-
2	All debugging tools	RL78, RX, RH850	Display of information on variables	-
3	All debugging tools	RL78, RX, RH850	Source files with the same name	-
4	All debugging tools	RL78	C++ facilities of CC-RL	-
5	All debugging tools	RL78, RX, RH850	Saving the States of Debug Tools	-

#### 6.1.2 Details of restrictions imposed by debugging tools

No.1 Division of load modules

**Applies to:** All debugging tools for RL78, RX, RH850

**Description:** The restrictions below apply when the CC-RH compiler is used to generate split load modules from a program.

a. Source-level debugging becomes impossible.

b. The second and subsequent output files are not automatically registered with the debugging tool.

**Workaround:** There is no workaround.

## No.2 Display of information on variables

**Applies to:** All debugging tools for RL78, RX, RH850

**Description:** If two or more variables defined in a function have the same name, the values of variables that can be viewed when the program has stopped may differ from the expected values. Whether this phenomenon arises depends on the optimization level\* selected during the process of compilation.

Note: The optimization level can be set via [Build Tool] – [Common Options] – [Frequently Used Options (Link)].

[Example] In the example below, char-type variable “a” is in the innermost scope at (\*1) and int-type variable “a” is in the innermost scope at (\*2). Under some conditions, however, only the value of one of the variables will be visible at (\*1) and (\*2).

```
void main()
{
    int a = 100;
    {
        char a = 'A';
        a++; <-(*1)
    }
    a++; <-(*2)
}
```

- Display of (\*1) in the [Watch] panel

“a” ‘A’ (0x41) “signed char” “0xefeb1004” // Expected value  
or “a” 100 (0x00000064) “int” “0xefeb1000”

- Display of (\*2) in the [Watch] panel

“a” ‘B’ (0x42) “signed char” “0xefeb1004”  
or “a” 100 (0x00000064) “int” “0xefeb1000” // Expected value

Condition: Optimization other than for debugging at the time of compilation.

**Workaround:** Select [Optimize for Debugging] as the optimization level before compilation.

No.3 Source files with the same name

**Applies to:** All debugging tools for RL78, RX, RH850

**Description:** When two or more files with the same name exist in a load module being debugged, line addresses are not displayed correctly in the editor. Setting of events also does not work correctly.

Example:

C:\Work\CS+\ProjA\ProjA.mtpj\Src\main.c -> A.abs

C:\Work\CS+\ProjB\ProjB.mtpj\Src\main.c -> B.abs

This is a case where the above two load modules are being debugged simultaneously.

**Note:** Although multiple load modules are used in the above example, this restriction is also applicable to cases where a single load module is in use.

[Conditions] The relative paths to the files from the compilation directory are the same (including the filenames).

Building by CS+

Project file directory (\*.mtpj) = compilation directory

Building by using a makefile

Current directory = compilation directory

**Workaround:** Source files with the same name can be distinguished in either of the following ways.

a. Change the configuration of the folders so that the relative paths to the files from the compilation directory differ.

Before: ProjA\Src\main.c

ProjB\Src\main.c

After: ProjA\SrcA\main.c

ProjB\SrcB\main.c

With this change, the relative paths will be as follows.

“SrcA\main.c”

“SrcB\main.c”

b. Change the names of the source files so that all of the files to be debugged have unique names.

Before: ProjA\Src\main.c

ProjB\Src\main.c

After: ProjA\Src\mainA.c

ProjB\Src\mainB.c

No.4 C++ facilities of CC-RL

**Applies to:** All debugging tools for RL78

**Description:** Symbols or functions implemented with the following C++ facilities cannot be debugged.

- Namespaces
- Derived classes
- Templates

**Workaround:** There is no workaround.

## No.5 Saving the States of Debug Tools

**Applies to:**

- Products with an internal RAM size [byte] of less than 16384 (16K) in the RX Family.

Product examples: RX110, RX111, RX130, RX13T, RX210, RX220, RX23T, RX62G, RX62T, RX63T

Products with a built-in RAM size [byte] of 16384 (16K) or more are not subject to this limitation even if they are the above products.

- RL78/G24 \* When the debug target is FAA.
- RH850 \* When the debug target is set to GTM.

**Description:** Save the debug tool states does not work. Errors may occur or CS+ response may be lost.

- If an error occurs, the following error message is displayed.

Error(E0210014) Failed to save RAM or register values to the file(<filename>).

[Direct Error Cause]

Exception of type 'System.OutOfMemoryException' was thrown.

- If the rewind feature is used, the following message may be output on the output panel.

Information(M0210002) : Failed to save RAM or register values for rewinding.

**Conditions:**

If any of the following operations are performed

- Select [Save debug tool state N] from [Save debug tool state] in the Debug menu.
- Click the save icon in [Target state save and load] on the toolbar.
- Run debugger.DebugTool.SaveState(fileName) in the Python console.

If any of the following operations are carried out \* The timing of occurrence is at the time of execution or execution stop.

- The action event is set in the [State save event] tab of the Action event dialog box.
- The rewind feature is enabled in the state save feature of the [General - Debug] category in the options dialog.

**Workaround:** There is no workaround.

## 6.2 Restrictions imposed by design tools

### 6.2.1 List of restrictions imposed by design tools

No.	Target tool	Target device	Description	Remarks
1	Code Generator	RH850	The project tree flickers when switching active project	-

### 6.2.2 Details of restrictions imposed by design tools

No.1 The project tree flickers when switching active project

**Applies to:** The design tool for RH850

**Description:** If there are two or more projects on project tree and each project contains [Code Generator], when switching active project from one to the other, the project tree flickers several seconds.

**Workaround:** There is no workaround.

**Revision Record**

Rev.	Date	Description	
		Page	Summary
Rev.1.00	Dec 01, 2025	-	First Edition issued

## Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation or any other use of the circuits, software, and information in the design of your product or system. Renesas Electronics disclaims any and all liability for any losses and damages incurred by you or third parties arising from the use of these circuits, software, or information.
  2. Renesas Electronics hereby expressly disclaims any warranties against and liability for infringement or any other claims involving patents, copyrights, or other intellectual property rights of third parties, by or arising from the use of Renesas Electronics products or technical information described in this document, including but not limited to, the product data, drawings, charts, programs, algorithms, and application examples.
  3. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
  4. You shall be responsible for determining what licenses are required from any third parties, and obtaining such licenses for the lawful import, export, manufacture, sales, utilization, distribution or other disposal of any products incorporating Renesas Electronics products, if required.
  5. You shall not alter, modify, copy, or reverse engineer any Renesas Electronics product, whether in whole or in part. Renesas Electronics disclaims any and all liability for any losses or damages incurred by you or third parties arising from such alteration, modification, copying or reverse engineering.
  6. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The intended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.
    - "Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; industrial robots; etc.
    - "High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control (traffic lights); large-scale communication equipment; key financial terminal systems; safety control equipment; etc.
- Unless expressly designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not intended or authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems; surgical implantations; etc.), or may cause serious property damage (space system; undersea repeaters; nuclear power control systems; aircraft control systems; key plant systems; military equipment; etc.). Renesas Electronics disclaims any and all liability for any damages or losses incurred by you or any third parties arising from the use of any Renesas Electronics product that is inconsistent with any Renesas Electronics data sheet, user's manual or other Renesas Electronics document.
7. No semiconductor product is absolutely secure. Notwithstanding any security measures or features that may be implemented in Renesas Electronics hardware or software products, Renesas Electronics shall have absolutely no liability arising out of any vulnerability or security breach, including but not limited to any unauthorized access to or use of a Renesas Electronics product or a system that uses a Renesas Electronics product. **RENESAS ELECTRONICS DOES NOT WARRANT OR GUARANTEE THAT RENESAS ELECTRONICS PRODUCTS, OR ANY SYSTEMS CREATED USING RENESAS ELECTRONICS PRODUCTS WILL BE INVULNERABLE OR FREE FROM CORRUPTION, ATTACK, VIRUSES, INTERFERENCE, HACKING, DATA LOSS OR THEFT, OR OTHER SECURITY INTRUSION ("Vulnerability Issues"). RENESAS ELECTRONICS DISCLAIMS ANY AND ALL RESPONSIBILITY OR LIABILITY ARISING FROM OR RELATED TO ANY VULNERABILITY ISSUES. FURTHERMORE, TO THE EXTENT PERMITTED BY APPLICABLE LAW, RENESAS ELECTRONICS DISCLAIMS ANY AND ALL WARRANTIES, EXPRESS OR IMPLIED, WITH RESPECT TO THIS DOCUMENT AND ANY RELATED OR ACCOMPANYING SOFTWARE OR HARDWARE, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY, OR FITNESS FOR A PARTICULAR PURPOSE.**
  8. When using Renesas Electronics products, refer to the latest product information (data sheets, user's manuals, application notes, "General Notes for Handling and Using Semiconductor Devices" in the reliability handbook, etc.), and ensure that usage conditions are within the ranges specified by Renesas Electronics with respect to maximum ratings, operating power supply voltage range, heat dissipation characteristics, installation, etc. Renesas Electronics disclaims any and all liability for any malfunctions, failure or accident arising out of the use of Renesas Electronics products outside of such specified ranges.
  9. Although Renesas Electronics endeavors to improve the quality and reliability of Renesas Electronics products, semiconductor products have specific characteristics, such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Unless designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not subject to radiation resistance design. You are responsible for implementing safety measures to guard against the possibility of bodily injury, injury or damage caused by fire, and/or danger to the public in the event of a failure or malfunction of Renesas Electronics products, such as safety design for hardware and software, including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult and impractical, you are responsible for evaluating the safety of the final products or systems manufactured by you.
  10. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. You are responsible for carefully and sufficiently investigating applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive, and using Renesas Electronics products in compliance with all these applicable laws and regulations. Renesas Electronics disclaims any and all liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
  11. Renesas Electronics products and technologies shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You shall comply with any applicable export control laws and regulations promulgated and administered by the governments of any countries asserting jurisdiction over the parties or transactions.
  12. It is the responsibility of the buyer or distributor of Renesas Electronics products, or any other party who distributes, disposes of, or otherwise sells or transfers the product to a third party, to notify such third party in advance of the contents and conditions set forth in this document.
  13. This document shall not be reprinted, reproduced or duplicated in any form, in whole or in part, without prior written consent of Renesas Electronics.
  14. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products.

(Note1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its directly or indirectly controlled subsidiaries.

(Note2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

(Rev.5.0-1 October 2020)

## Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu,  
Koto-ku, Tokyo 135-0061, Japan  
[www.renesas.com](http://www.renesas.com)

## Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.

## Contact information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit: [www.renesas.com/contact/](http://www.renesas.com/contact/).