

RZ MPU HTML5 (Chromium109) Package V1.0.1 for RZ/V Verified Linux Package V3.0.7

R01US0747EJ0101

Rev. 1.01

July. 31, 2025

HTML5(Chromium) Start-up Guide

Introduction

This release note describes the contents, building procedures for HTML5 (Chromium109) and important points of the RZ MPU HTML5 (Chromium109) Package V1.0.1 for RZ/V Verified Linux Package (hereinafter referred to as “VLP/V”).

If you need information to build Linux BSPs without a GUI Framework of HTML5, please refer to “RZ/V Verified Linux Package Version 3.0.7 Release Note” (r01us0565ej0109-rz-v(Release Note).pdf.

Contents

1. Release Items	2
2. Build Instructions	5
2.1 Build VLP without HTML5	5
2.2 Building images enabling HTML5.....	6
2.3 Browser application	8
2.3.1 Launch the browser application on the evaluation board	8
3. Note	9
4. Revision History	9

1. Release Items

- **Name and version**

RZ MPU HTML5 (Chromium109) Package V1.0.1 for RZ/V Verified Linux Package Version 3.0.7 (hereinafter referred to as “HTML5 (Chromium109) Package v1.0.1” and “VLP/V v3.0.7”)

- **Distribution method**

Please visit the site below and create an account to download the packages. This site is for the entire RZ Family which includes the RZ/V series. Basic packages of VLP/V can be downloaded.

RZ Family:

<https://www.renesas.com/products/microcontrollers-microprocessors/rz-arm-based-high-end-32-64-bit-mpus>

You can also download the basic packages of VLP/V v3.0.7 from the site below.

RZ/V Verified Linux Package [5.10-CIP]:

<https://www.renesas.com/us/en/software-tool/rzv-verified-linux-package-510-cip>

- **Target board for HTML5 (Chromium109)**

RZ/V2L Evaluation Board Kit PMIC version (*):

- RZ/V2L SMARC Module Board v2.1
- RZ SMARC Series Carrier Board v4.0

(*) “RZ/V2L Evaluation Board Kit” and “RZV2L Evaluation Board Kit PMIC version” includes the RZ/V2L SMARC Module Board and the RZ SMARC Series Carrier Board.

- **File contents**

VLP/V is delivered by the files listed in Table 1.

RZ MPU HTML5 (Chromium109) Package V1.0.1 for RZ/V Verified Linux Package V3.0.7 Chromium Start-up Guide

Table 1. RZ/G Verified Linux Package

Basic files of VLP/V v3.0.7

File	Description
RTK0EF0045Z0024AZJ-v3.0.7.zip (*)	Verified Linux Package. This file includes the Yocto recipe packages and the necessary documents.
rzv_vlp_v3.0.7.tar.gz	Yocto recipe packages
r01us0565ej0109-rz-v(Release Note).pdf	Release Note of VLP without a GUI Framework of HTML5.
r01us0617ej0105-rz-v(Linux Start-up Guide RZV2L) .pdf	Document Release Note of VLP without a GUI Framework of HTML5 describing booting method and the required settings of bootloader for RZ/V2L .
oss_pkg_rzv_v3.0.7.7z (*)	Open source software packages See the Note below before you download.

Basic files of HTML5 (Chromium109) Package v1.0.0

File	Description
RTK0EF0193Z00001ZJ_v1.0.1.zip (*)	Verified Linux Package for HTML5 (Chromium109). This file includes the Yocto recipe packages for HTML5 (Chromium109) and the necessary documents.
rzv_bsp_chromium109_v1.0.1.tar.gz	Yocto recipe packages
r01us0747ej0101-rz-v(Chromium Start-up Guide).pdf	This document
oss_pkg_chromium109_v1.0.0_forVLPVv3.0.7.7z (*)	Open source software packages for HTML5 (Chromium109). Please use this file instead of oss_pkg_rzv_v3.0.7.7z when building HTML5 (Chromium109). See the Note below before download.

(*) Yocto recipe and Open source software packages are provided “AS IS” with no warranty and the license which is described in the source code. Please check the contents of the license, then consider the applicability to the product carefully.

Note) Open source software packages contain all source codes of OSSs except for Linux kernel. These are the same versions of OSSs used when VLP/V was verified. If you are just evaluating VLP/V and RZ/V series, open source software packages are not mandatory to use. Usually, all the software can be built without using these files if your build machine is connected to the Internet. Open source software packages are required for an “offline” environment. The word “offline” means an isolated environment which does not connect to any network. VLP/V can always build images in this “offline” environment by using these packages without affected from changes of original repositories of OSSs. Also, this “offline” environment always reproduces the same images as the images which were verified by Renesas. Note that if you build without using open source software packages, there are possibilities to use different source codes than Renesas used due to the implicit changes of the repositories of OSSs.

Optional packages (*1, 2)

	File ("XX" is replaced by "EN" or "JP".)	Description
RZ MPU Graphics Library	RTK0EF0045Z14001ZJ-v3.1.2.3_XX.zip	RZ MPU Graphics Library for RZ/G2L, RZ/G2LC and RZ/V2L . This provides graphics function compliant with the OpenGL ES standard. These libraries are tested with VLP/V v3.0.7.
RZ MPU Video Codec Library	RTK0EF0045Z16001ZJ-v3.1.3.0_XX.zip	RZ MPU Video Codec Library for RZ/G2L, RZ/V2L . These libraries are tested with VLP/V v3.0.7.

2. Build Instructions

2.1 Build VLP without HTML5

Please follow the below documents and build the VLP firstly. You can read the release note and check the release items. You can build VLP by following the chapter 1 and 2 of the Linux Start-up guide.

Table 2. Documents for the first step

r01us0565ej0109-rz-v(Release Note).pdf	Release Note of VLP without a GUI Framework of HTML5. You can check the release items.
r01us0617ej0105-rz-v(Linux Start-up Guide RZV2L).pdf	Documents describing booting method and the required settings of bootloader for RZ/V2L . Please refer to the chapter 1 and 2 for building VLP.

Please note that it is necessary to run the below command in the step 2.2(6) of the Linux Start-up guide:

\$ MACHINE=smarc-rzv2l bitbake core-image-weston
--

HTML5 (Chromium109) supports only core-image-weston for the build image.

And VLP has some additional packages and options, so users can select the combination themselves and build. Please note that HTML5 (Chromium109) packages are tested with the below combination, so please build with the below combination for HTML5 (Chromium109).

Example) RZ/V2L is tested using both the graphics library and the codec library, but it is not tested using Security, MultiOS, and Docker.

Table 3. Combinations of HTML5

		Packages and Option				
		Graphics	Codec	Security	MultiOS	Docker
Devices	RZ/V2L	O		-	-	-

(*) “-” means that the packages and the option are not tested with HTML5.

After you complete the build, please move to the section 2.2 in this document and enable HTML5 (Chromium109).

2.2 Building images enabling HTML5

This section describes the instructions to enable HTML5 (Chromium109) to the build images.

Copy all files obtained from Renesas into your Linux Host PC prior to the steps below. The directory which you put the files in is described as <package download directory> in the build instructions.

(1) Move to a working directory at your home directory, and decompress Yocto recipe package

Run the commands below. The name and the place of the working directory can be changed as necessary.

```
$ cd ~/rzv_vlp_v3.0.7
$ cp ../<package download directory>/*.zip .
$ unzip ./RTK0EF0193Z00000ZJ_v1.0.1.zip
$ tar zxvf ./RTK0EF0193Z00000ZJ_v1.0.1/rzv_bsp_chromium109_v1.0.1.tar.gz
```

(2) Setup a build environment

Initialize a build using the 'oe-init-build-env' script in Poky and point TEMPLATECONF to platform conf path.

```
$ TEMPLATECONF=$PWD/meta-renesas/meta-rzv21/docs/template/conf/ source \
poky/oe-init-build-env build
```

(3) Add layers

Please follow the below steps to add the layers you need. The steps add the settings to bblayers.conf.

```
$ bitbake-layers add-layer ../meta-clang
$ bitbake-layers add-layer ../meta-browser/meta-chromium
$ bitbake-layers add-layer ../meta-openembedded/meta-networking
$ bitbake-layers add-layer ../meta-browser-hwdecode
```

(4) Enable HTML5 (Chromium109)

Please follow the following instructions to edit the configuration file and enable HTML5 (Chromium109).

- Add the below lines to "~/rzv_vlp_v3.0.7/build/conf/local.conf".

```
IMAGE_INSTALL_append = " chromium-ozone-wayland "
IMAGE_INSTALL_append = " ntp "
IMAGE_INSTALL_append = " ttf-sazanami-gothic ttf-sazanami-mincho "
IMAGE_INSTALL_append = " adwaita-icon-theme-cursors "
IMAGE_INSTALL_append = " v4l-gst "
PREFERRED_VERSION_nodejs-native = "14.%"
```

(5) Decompress OSS files to “build” directory (Optional)

Run the commands below. This step is not mandatory and able to go to the step (6) in case the “offline” environment is not required. All OSS packages will be decompressed with this '7z' command.

If this step is omitted and BB_NO_NETWORK is set to “0” in the step (6), all source codes will be downloaded from the repositories of each OSS via the internet when running bitbake command. Please note that if you do not use an “offline” environment, a build may fail due to the implicit changes of the repositories of OSS.

```
$ cp ../../<package download directory>/*.7z .
$ 7z x ~/ oss_pkg_chromium109_v1.0.1.7z
```

When you run the 7z command, you may see the bellow message. Please select “A” at that time.

```
Would you like to replace the existing file:
Path: ./downloads/git2_github.com.gorilla.context.git.tar.gz.done
Size: 0 bytes
Modified: 20XX-XX-XX XX:XX:XX
with the file from archive:
Path: downloads/git2_github.com.gorilla.context.git.tar.gz.done
Size: 0 bytes
Modified: 20XX-XX-XX XX:XX:XX
? (Y)es / (N)o / (A)lways / (S)kip all / A(u)to rename all / (Q)uit? A
```

After the above procedure is finished, the “offline” environment is ready. If you want to prevent network access, please change the line in the “~/rzg_vlp_v3.0.6/build/conf/local.conf” as below:

```
BB_NO_NETWORK = "1"
```

To change BB_NO_NETWORK from “0” to “1”.

After the above procedure is finished, the “offline” environment is ready.

(6) Start a build

Run the commands below to start a build. Building an image can take up to a few hours depending on the user’s host system performance.

Build the target file system image using bitbake

```
$ MACHINE=smarc-rzv2l bitbake core-image-weston
```

After the build is successfully completed, a similar output will be seen, and the command prompt will return.

```
NOTE: Tasks Summary: Attempted 7427 tasks of which 16 didn't need to be rerun and all succeeded.
```

All necessary will be generated by the bitbake command and will be located in the **build/tmp/ deploy/images** directory.

2.3 Browser application

This section describes how to launch and configure the browser application after building VLP.

2.3.1 Launch the browser application on the evaluation board

(1) Prepare the SD card and boot the evaluation board

Please follow the below documents again to boot the evaluation board. You can prepare the SD card and boot the evaluation board by following the chapter 3 and 4 of the Linux Start-up guide.

After booting the target board, please move to the next section 2.3.1(2) in this document.

Table 4. Documents for the first step

r01us0617ej0105-rz-v(Linux Start-up Guide RZV2L).pdf	Documents describing booting method and the required settings of bootloader for RZ/V2L . Please refer to the chapter 3 and 4.
--	--

(2) Launch the browser application on the evaluation board

Please connect an USB hub, a mouse, and a keyboard to your evaluation board. Then please run the below command on Tera Term.

“https://~~~” means a website URL, so please enter the URL of the site you want to open. “/home/root/xxx.html” means a html content in the root file system, so please enter the path of the file you want to open.

```
$ chromium https://~~~
$ chromium /home/root/xxx.html
```


3. Note

(1) Test Status of the HTML5 (Chromium109) package

The HTML5 (Chromium109) package is tested. Two types of tests are conducted.

- web-platform-tests:
This is to test functions which the browser application have in detail.
- Performance tests:
Based on <https://github.com/webdino/gecko-embedded/wiki/QA>, the performance of the browser application is tested.

4. Revision History

Rev.	Date	Description	
		Page	Summary
1.00	July. 31, 2024	-	First edition for VLP/V v3.0.6.
1.01	July. 31, 2025	-	First edition for VLP/V v3.0.7.

Website and Support

Renesas Electronics Website

<http://www.renesas.com/>

Inquiries

<http://www.renesas.com/contact/>

All trademarks and registered trademarks are the property of their respective owners.