



Report No. APR-25-H0149
Date: Apr. 1, 2026

RENESAS SEMICONDUCTOR RELIABILITY REPORT

SERIES: REXFET-1 100V

DEVICE: Refer to Product List

QUALITY GRADE: High Quality

Quality Assurance Div.
Renesas Electronics Corporation

Notice

- 1 Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation or any other use of the circuits, software, and information in the design of your product or system. Renesas Electronics disclaims any and all liability for any losses and damages incurred by you or third parties arising from the use of these circuits, software, or information.
 - 2 Renesas Electronics hereby expressly disclaims any warranties against and liability for infringement or any other claims involving patents, copyrights, or other intellectual property rights of third parties, by or arising from the use of Renesas Electronics products or technical information described in this document, including but not limited to, the product data, drawings, charts, programs, algorithms, and application examples.
 - 3 No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
 - 4 You shall be responsible for determining what licenses are required from any third parties, and obtaining such licenses for the lawful import, export, manufacture, sales, utilization, distribution or other disposal of any products incorporating Renesas Electronics products, if required.
 - 5 You shall not alter, modify, copy, or reverse engineer any Renesas Electronics product, whether in whole or in part. Renesas Electronics disclaims any and all liability for any losses or damages incurred by you or third parties arising from such alteration, modification, copying or reverse engineering.
 - 6 Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The intended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.

"Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; industrial robots; etc.

"High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control (traffic lights); large-scale communication equipment; key financial terminal systems; safety control equipment; etc.

Unless expressly designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not intended or authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems; surgical implantations; etc.), or may cause serious property damage (space system; undersea repeaters; nuclear power control systems; aircraft control systems; key plant systems; military equipment; etc.). Renesas Electronics disclaims any and all liability for any damages or losses incurred by you or any third parties arising from the use of any Renesas Electronics product that is inconsistent with any Renesas Electronics data sheet, user's manual or other Renesas Electronics document.
 - 7 No semiconductor product is absolutely secure. Notwithstanding any security measures or features that may be implemented in Renesas Electronics hardware or software products, Renesas Electronics shall have absolutely no liability arising out of any vulnerability or security breach, including but not limited to any unauthorized access to or use of a Renesas Electronics product or a system that uses a Renesas Electronics product. RENESAS ELECTRONICS DOES NOT WARRANT OR GUARANTEE THAT RENESAS ELECTRONICS PRODUCTS, OR ANY SYSTEMS CREATED USING RENESAS ELECTRONICS PRODUCTS WILL BE INVULNERABLE OR FREE FROM CORRUPTION, ATTACK, VIRUSES, INTERFERENCE, HACKING, DATA LOSS OR THEFT, OR OTHER SECURITY INTRUSION ("Vulnerability Issues"). RENESAS ELECTRONICS DISCLAIMS ANY AND ALL RESPONSIBILITY OR LIABILITY ARISING FROM OR RELATED TO ANY VULNERABILITY ISSUES. FURTHERMORE, TO THE EXTENT PERMITTED BY APPLICABLE LAW, RENESAS ELECTRONICS DISCLAIMS ANY AND ALL WARRANTIES, EXPRESS OR IMPLIED, WITH RESPECT TO THIS DOCUMENT AND ANY RELATED OR ACCOMPANYING SOFTWARE OR HARDWARE, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY, OR FITNESS FOR A PARTICULAR PURPOSE.
 - 8 When using Renesas Electronics products, refer to the latest product information (data sheets, user's manuals, application notes, "General Notes for Handling and Using Semiconductor Devices" in the reliability handbook, etc.), and ensure that usage conditions are within the ranges specified by Renesas Electronics with respect to maximum ratings, operating power supply voltage range, heat dissipation characteristics, installation, etc. Renesas Electronics disclaims any and all liability for any malfunctions, failure or accident arising out of the use of Renesas Electronics products outside of such specified ranges.
 - 9 Although Renesas Electronics endeavors to improve the quality and reliability of Renesas Electronics products, semiconductor products have specific characteristics, such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Unless designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not subject to radiation resistance design. You are responsible for implementing safety measures to guard against the possibility of bodily injury, injury or damage caused by fire, and/or danger to the public in the event of a failure or malfunction of Renesas Electronics products, such as safety design for hardware and software, including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult and impractical, you are responsible for evaluating the safety of the final products or systems manufactured by you.
 - 10 Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. You are responsible for carefully and sufficiently investigating applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive, and using Renesas Electronics products in compliance with all these applicable laws and regulations. Renesas Electronics disclaims any and all liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
 - 11 Renesas Electronics products and technologies shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You shall comply with any applicable export control laws and regulations promulgated and administered by the governments of any countries asserting jurisdiction over the parties or transactions.
 - 12 It is the responsibility of the buyer or distributor of Renesas Electronics products, or any other party who distributes, disposes of, or otherwise sells or transfers the product to a third party, to notify such third party in advance of the contents and conditions set forth in this document.
 - 13 This document shall not be reproduced or duplicated in any form or disclosed to any third party, in whole or in part, without prior written consent of Renesas Electronics.
 - 14 Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products.
- (Note 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its directly or indirectly controlled subsidiaries.
- (Note 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

(Rev.5.0-2 October 2020)

Q101 Qualification Test Results for Product List

[Note : Basically qualification tests were performed using a representative product with the same wafer process and the same package structure.]

APR-25-H0149

Test	#	Reference	Test Conditions	Lots	S.S.	Total	Results (Fail of Total)	Comments: (N/A =Not Applicable)
------	---	-----------	-----------------	------	------	-------	----------------------------	------------------------------------

TEST GROUP A – ACCELERATED ENVIRONMENT STRESS TESTS

PC	A1	JESD22-A113 J-STD-020	SMD only; Moisture Preconditioning for HAST/H3TRB, UHAST/AC, TC, IOL/PTC.	3	308	924	0 of 924	MSL1
HAST	A2	JESD22-A110	Ta=130C, RH=85%, VDSS Maximum rating, 96h	3	77	231	0 of 231	Performed on Package Type : SO8-FL, μ SO8-FL See H3TRB, Package Type : TOLL, TOLG, TOLT
H3TRB	A2 alt	JESD22-A101	Ta=85C, RH=85%, VDSS Maximum rating, 1000h	3	77	231	0 of 231	Performed on Package Type : TOLL, TOLG, TOLT See HAST, Package Type : SO8-FL, μ SO8-FL
UHAST	A3	JESD22-A118 or A101	Ta=130C, RH=85%, 96h	3	77	231	0 of 231	-
AC	A3 alt	JESD22-A102	Ta=121C, RH=100%, 96h	-	-	-	-	See UHAST.
TC	A4	JESD22-A104 Appendix 6	Ta=-55C to 150C, 1000cycles	3	77	231	0 of 231	-
TCHT	A4a	JESD22-A104 Appendix 6	TC Hot Test.	-	-	-	-	See TCDT.
TCDT	A4a alt	JESD22-A104 Appendix 6 J-STD-035	TC Delamination Test.	3	77	231	0 of 231	Performed on Package Type : TOLL, TOLG, TOLT, μ SO8-FL N/A, Package Type : SO8-FL (Not wire, clip bond)
IOL	A5	MIL-STD-750 Method 1037	Δ Te=100C, 15000cycles	3	77	231	0 of 231	-
PTC	A5 alt	JESD22-A105	Power Temperature Cycling.	-	-	-	-	See IOL.

TEST GROUP B – ACCELERATED LIFETIME SIMULATION TESTS

HTRB	B1	MIL-STD-750-1 M1039	Tj(Tch)= 175C, VDSS Maximum rating, 1000h	3	77	231	0 of 231	-
ACBV	B1a	MIL-STD-750-1 M1040 Test condition A	AC blocking voltage.	-	-	-	-	N/A Thyristors Only.
SSOP	B1b	MIL-STD-750-1 M1038 condition B (Zeners)	Steady State Operational.	-	-	-	-	N/A Voltage Regulators (Zeners) Only.
HTGB	B2	JESD22-A108	Tj(Tch)= 175C, VGSS=+20V, 1000h	3	77	231	0 of 231	-

(C)Renesas Electronics Corporation. All rights reserved.

Test	#	Reference	Test Conditions	Lots	S.S.	Total	Results (Fail of Total)	Comments: (N/A =Not Applicable)
------	---	-----------	-----------------	------	------	-------	----------------------------	------------------------------------

TEST GROUP C – PACKAGE ASSEMBLY INTEGRITY TESTS

DPA	C1	AEC Q101-004 Section4	Random sample of parts that have successfully completed H3TRB or HAST and TC.	3	4	12	0 of 12	-
PD	C2	JEDEC JESD22-B100	Physical Dimensions.	1	30	30	0 of 30	-
WBP	C3	MIL-STD-750-2 Method 2037	Wire Bond Pull.	1bond	10parts	10bonds	0 of 10bonds	Performed on Package Type : TOLL, TOLG, TOLT, μ SO8-FL N/A, Package Type : SO8-FL (Not wire, clip bond)
WBS	C4	AEC Q101-003 JESD22-B116	Wire Bond Shear Test.	1bond	10parts	10bonds	0 of 10bonds	Performed on Package Type : TOLL, TOLG, TOLT, μ SO8-FL N/A, Package Type : SO8-FL (Not wire, clip bond)
DS	C5	MIL-STD-750-2 Method 2017	Die Shear.	1	5	5	0 of 5	Performed on Package Type : TOLL, TOLG, TOLT N/A, Package Type : SO8-FL, μ SO8-FL (Die shear not possible)
TS	C6	MIL-STD-750-2 Method 2036	Terminal Strength.	-	-	-	-	N/A Through-hole leaded parts only.
RTS	C7	JESD22-B107	Resistance to Solvents.	-	-	-	-	N/A Not required for laser etched parts.
RSH	C8	JESD22-A111 (SMD)	Resistance to Solder Heat.	-	-	-	-	N/A Wave solder deprecated.
TR	C9	JESD24-3, 24-4, 24- 6 as appropriate	Thermal Resistance.	1	10	10	0 of 10	-
SD	C10	JEDEC J-STD-002	Solderability: (>95% coverage)	3	10	30	0 of 30	-
WG	C11	AEC Q005	see AEC-Q005	-	-	-	Pass	Performed on product TEG with test method based on JESD201.
CA	C12	MIL-STD-750-2 Method 2006	Constant Acceleration.	-	-	-	-	N/A Hermetic packaged devices only
VVF	C13	JESD22-B103	Vibration Variable Frequency.	-	-	-	-	N/A Hermetic packaged devices only
MS	C14	JESD22-B104	Mechanical Shock.	-	-	-	-	N/A Hermetic packaged devices only
HER	C15	JEDEC JESD22-A109	Hermeticity.	-	-	-	-	N/A Hermetic packaged devices only

Test	#	Reference	Test Conditions	Lots	S.S.	Total	Results (Fail of Total)	Comments: (N/A =Not Applicable)
------	---	-----------	-----------------	------	------	-------	----------------------------	------------------------------------

TEST GROUP D – DIE FABRICATION RELIABILITY TESTS

DI	D1	AEC Q101-004 Section3	Dielectric Integrity.	1	5	5	0 of 5	Verified by process TEG
----	----	--------------------------	-----------------------	---	---	---	--------	-------------------------

TEST GROUP E – ELECTRICAL VERIFICATION TESTS

EV	E0	JESD22-B101	External Visual.	All	All	All	0 of All	-
TEST	E1	User/Supplier Specification	Pre and Post Stress Electrical Test.	All	All	All	0 of All	-
PV	E2	Individual AEC user specification	Parametric Verification.	3	25	75	0 of 75	-
ESDH	E3	AEC Q101-001	Electrostatic Discharge, Human Body Model.	1	30	30	0 of 30	HBM: C:100pF, R:1.5KΩ See product list for withstand voltage.
ESDC	E4	AEC Q101-005	Electrostatic Discharge, Charged Device Model.	1	30	30	0 of 30	CDM: Over 1000V
UIS	E5	AEC Q101-004 Section2	UNCLAMPED INDUCTIVE SWITCHING.	1	5	5	0 of 5	-
SC	E6	AEC Q101-006	Short Circuit Characterization.	-	-	-	-	N/A Smart power parts only.

Table. Product list

APR-25-H0149

No	Product part number	Package Type	HBM withstand voltage
1	RBA300N10EANS-3UA02#GB0	TOLL	2000V to \leq 4000V
2	RBA019N10R1SBQ4#GB0	TOLL	2000V to \leq 4000V
3	RBA300N10EHPF-5UA02#GB0	TOLG	2000V to \leq 4000V
4	RBA012N10R1SBPW#KB0	TOLT	2000V to \leq 4000V
5	RBA015N10R1SBPW#KB0	TOLT	2000V to \leq 4000V
6	RBA019N10R1SBPW#KB0	TOLT	2000V to \leq 4000V
7	RBA160N10EANS-4UA03#HB0	SO8-FL(5×6)	2000V to \leq 4000V
8	RBA130N10EANS-4UA04#HB0	SO8-FL(5×6)	2000V to \leq 4000V
9	RBA80N10EANS-4UA07#HB0	SO8-FL(5×6)	1000V to \leq 2000V
10	RBA40N10EANS-5UA11#HB0	μ SO8-FL(3×3)	1000V to \leq 2000V
11	RBA20N10EANS-5UA21#HB0	μ SO8-FL(3×3)	500V to \leq 1000V
12			
13			
14			
15			
16			
17			
18			
19			
20			
21			
22			
23			
24			
25			
26			
27			
28			
29			
30			
31			
32			
33			
34			
35			
36			
37			
38			
39			
40			
41			
42			
43			
44			
45			
46			
47			
48			
49			
50			