

IGBT

Design Considerations for Short Circuit Withstand Time (t_{sc})

Introduction

This document explains the design considerations for the short-circuit withstand time (t_{sc}) of Renesas IGBTs.

Contents

1. Load Short-Circuit Test.....	2
2. Renesas Design Concepts	3
2.1 Mode A: Breakdown Immediately Following Short Circuit	3
2.2 Mode B: Breakdown During ON Period	3
2.3 Mode C: Breakdown at Turn-off	4
2.4 Mode D: Thermal Runaway After Turn-off	4
3. Indirect Control of t_{sc}	4
Revision History	6

1. Load Short-Circuit Test

Elements used for bridge circuits such as inverters must include a short circuit (overcurrent) protection circuit that withstands conditions and prevents breakdown for the period until the gate voltage is cut off, even if the set is short circuited.

The length of withstand time in the event of a short circuit differs from product to product and must be verified with a load short-circuit test.

Figure 1.1 shows the short circuit used for the load short-circuit test.

A specified voltage is applied between the collector and emitter, and a pulse is applied between the gate and emitter to turn the IGBT on for a specified time. (Click [Load Short Measurement Method](#) for details on load short-circuit test method.)

During this ON period, a large current flows between the collector and emitter, and the load short-circuit withstand time (t_{sc}) is defined by Renesas as the on-time from the 10% point at which the collector current starts to flow to the 10% point at which it is cut off. (See Figure 1-2.)

The t_{sc} value is an important characteristic that indicates a product's robustness and reliability.




Figure 1-1 Short Circuit Used for the Load Short-circuit Test




Figure 1-2 Simplified Example of Short-circuit Wave Form

2. Renesas Design Concepts

Figure 2-1 shows the breakdown points confirmed by the load short-circuit test.

Typical short-circuit breakdown points are after the short circuit (Mode A), during the ON period (Mode B), at turn-off (Mode C), and after turn-off (Mode D).

Products with short-circuit withstand capability are designed to cut off current without device damage (including breakdown after turn-off in Mode D) by meeting data sheet conditions and remaining within the t_{sc} range.

Renesas adjusts the IGBT current capability and other specifications so that breakdown modes A through C do not occur before current is cut off.

For Mode D, Renesas also verifies that the short-circuit withstanding time for which current can be cut off has ample margin for t_{sc} , while considering process variations.

Products that are not covered by a short-circuit guarantee tend to break down early on in failure modes A and B. This increases the risk of a short circuit during actual operation. Exercise caution when selecting products, as use of such products in applications that are sensitive to short-circuit events can be extremely hazardous.




Figure 2-1 Breakdown Points in Short-Circuit Test

2.1 Mode A: Breakdown Immediately Following Short Circuit

As shown in Figure 2-1, Mode A indicates “breakdown immediately following short circuit.”

This type of breakdown is usually caused by latch-up due to surge current.

Renesas IGBTs are designed with a sufficient margin for each parameter to prevent surge currents, ensuring they do not reach the Mode A breakdown point.

2.2 Mode B: Breakdown During ON Period

Mode B indicates “breakdown during the ON period.”

This type of breakdown can result in latch-up due to excessive current and the formation of hot spots within the components/cells.

Renesas IGBTs are designed with a homogeneous cell layout and a sufficient margin to prevent latch-up so that they do not incur Mode B breakdown.

2.3 Mode C: Breakdown at Turn-off

Mode C indicates “breakdown at turn-off.”

This type of breakdown is usually caused by latch-up triggered by excessive off-surge voltage or rapid turn-off.

Renesas IGBTs are designed with appropriate wafer thickness and a sufficient margin to prevent latch-up so that they do not incur Mode C breakdown.

2.4 Mode D: Thermal Runaway After Turn-off

Mode D indicates “thermal runaway after turn-off.”

This type of breakdown is mainly caused by thermal runaway due to leakage currents that occur during the X period shown in Figure 2-1.

Renesas IGBTs are designed with optimal wafer thickness and threshold $V_{GE(th)}$ that guarantee the appropriate t_{sc} to prevent Mode D breakdown.

3. Indirect Control of t_{sc}

In general, verification of short-circuit withstand t_{sc} cannot be done during the screening of wafer tests.

Therefore, we conduct “indirect control of t_{sc} ” at the design stage.

Wafer thickness correlates with t_{sc} , as shown in Figure 3-1.

We set the optimum wafer thickness to provide a sufficient margin for the guaranteed t_{sc} value as stated in the datasheet.

As shown in Figure 3-2, the lower the $V_{GE(th)}$, the higher the short-circuit current I_C and the shorter the t_{sc} .

Renesas has conducted load short-circuit tests on corner samples with $V_{GE(th)}$ and confirmed that there is an optimum margin for t_{sc} specifications even for samples with low $V_{GE(th)}$.

Short-circuit withstand time t_{sc} , is an important indicator of IGBT robustness.

The relationship between t_{sc} and Si heat capacity C , and applied power W , is given by equation (1).

$$t_{sc} \propto \frac{C}{W} \quad (1)$$

Since heat capacity C is the product of wafer thickness z and die size A ,

and W is the product of $I_{C\ sat}$ and $V_{cc\ max}$, equation (1) can be expressed by equation (2).

$$t_{sc} \propto \frac{z \times A}{I_{C\ sat} \times V_{cc\ max}} \quad (2)$$

Furthermore, since $I_{C\ sat}$ correlates with $V_{GE(th)}$, t_{sc} includes the parameters of wafer thickness z and $V_{GE(th)}$, as shown in equation (3).

$$t_{sc} \propto \frac{z}{V_{GE(th)}} \times \frac{A}{V_{cc\ max}} \quad (3)$$

Z: wafer thickness, A: die size

Therefore, wafer thickness z and $V_{GE(th)}$ are important trade-off parameters for t_{sc} , a measure of robustness.

Renesas IGBTs are designed to optimize the parameters of wafer thickness and $V_{GE(th)}$, ensuring a design that achieves a sufficient t_{sc} margin.

By performing tolerance design verification of characteristic items and process parameters that correlate with the short-circuit withstand t_{sc} , we can satisfy the t_{sc} specification during product development.

At Renesas, we implement this method to indirectly control t_{sc} and provide safer products.




Figure 3-1 Relationship Between t_{sc} and Wafer Thickness and Short-circuit Waveform Examples




Figure 3-2 Relationship Between t_{sc} and $V_{GE(th)}$ and Short-circuit Waveform Examples

Revision History

Rev.	Date	Description	
		Page	Summary
1.00	Nov.19.2024	-	First edition

Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation or any other use of the circuits, software, and information in the design of your product or system. Renesas Electronics disclaims any and all liability for any losses and damages incurred by you or third parties arising from the use of these circuits, software, or information.
2. Renesas Electronics hereby expressly disclaims any warranties against and liability for infringement or any other claims involving patents, copyrights, or other intellectual property rights of third parties, by or arising from the use of Renesas Electronics products or technical information described in this document, including but not limited to, the product data, drawings, charts, programs, algorithms, and application examples.
3. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
4. You shall be responsible for determining what licenses are required from any third parties, and obtaining such licenses for the lawful import, export, manufacture, sales, utilization, distribution or other disposal of any products incorporating Renesas Electronics products, if required.
5. You shall not alter, modify, copy, or reverse engineer any Renesas Electronics product, whether in whole or in part. Renesas Electronics disclaims any and all liability for any losses or damages incurred by you or third parties arising from such alteration, modification, copying or reverse engineering.
6. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The intended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.

"Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; industrial robots; etc.

"High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control (traffic lights); large-scale communication equipment; key financial terminal systems; safety control equipment; etc.

Unless expressly designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not intended or authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems; surgical implantations; etc.), or may cause serious property damage (space system; undersea repeaters; nuclear power control systems; aircraft control systems; key plant systems; military equipment; etc.). Renesas Electronics disclaims any and all liability for any damages or losses incurred by you or any third parties arising from the use of any Renesas Electronics product that is inconsistent with any Renesas Electronics data sheet, user's manual or other Renesas Electronics document.

7. No semiconductor product is absolutely secure. Notwithstanding any security measures or features that may be implemented in Renesas Electronics hardware or software products, Renesas Electronics shall have absolutely no liability arising out of any vulnerability or security breach, including but not limited to any unauthorized access to or use of a Renesas Electronics product or a system that uses a Renesas Electronics product. RENESAS ELECTRONICS DOES NOT WARRANT OR GUARANTEE THAT RENESAS ELECTRONICS PRODUCTS, OR ANY SYSTEMS CREATED USING RENESAS ELECTRONICS PRODUCTS WILL BE INVULNERABLE OR FREE FROM CORRUPTION, ATTACK, VIRUSES, INTERFERENCE, HACKING, DATA LOSS OR THEFT, OR OTHER SECURITY INTRUSION ("Vulnerability Issues"). RENESAS ELECTRONICS DISCLAIMS ANY AND ALL RESPONSIBILITY OR LIABILITY ARISING FROM OR RELATED TO ANY VULNERABILITY ISSUES. FURTHERMORE, TO THE EXTENT PERMITTED BY APPLICABLE LAW, RENESAS ELECTRONICS DISCLAIMS ANY AND ALL WARRANTIES, EXPRESS OR IMPLIED, WITH RESPECT TO THIS DOCUMENT AND ANY RELATED OR ACCOMPANYING SOFTWARE OR HARDWARE, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY, OR FITNESS FOR A PARTICULAR PURPOSE.
8. When using Renesas Electronics products, refer to the latest product information (data sheets, user's manuals, application notes, "General Notes for Handling and Using Semiconductor Devices" in the reliability handbook, etc.), and ensure that usage conditions are within the ranges specified by Renesas Electronics with respect to maximum ratings, operating power supply voltage range, heat dissipation characteristics, installation, etc. Renesas Electronics disclaims any and all liability for any malfunctions, failure or accident arising out of the use of Renesas Electronics products outside of such specified ranges.
9. Although Renesas Electronics endeavors to improve the quality and reliability of Renesas Electronics products, semiconductor products have specific characteristics, such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Unless designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not subject to radiation resistance design. You are responsible for implementing safety measures to guard against the possibility of bodily injury, injury or damage caused by fire, and/or danger to the public in the event of a failure or malfunction of Renesas Electronics products, such as safety design for hardware and software, including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult and impractical, you are responsible for evaluating the safety of the final products or systems manufactured by you.
10. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. You are responsible for carefully and sufficiently investigating applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive, and using Renesas Electronics products in compliance with all these applicable laws and regulations. Renesas Electronics disclaims any and all liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
11. Renesas Electronics products and technologies shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You shall comply with any applicable export control laws and regulations promulgated and administered by the governments of any countries asserting jurisdiction over the parties or transactions.
12. It is the responsibility of the buyer or distributor of Renesas Electronics products, or any other party who distributes, disposes of, or otherwise sells or transfers the product to a third party, to notify such third party in advance of the contents and conditions set forth in this document.
13. This document shall not be reprinted, reproduced or duplicated in any form, in whole or in part, without prior written consent of Renesas Electronics.
14. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products.

(Note1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its directly or indirectly controlled subsidiaries.

(Note2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

(Rev.5.0-1 October 2020)

Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu,
Koto-ku, Tokyo 135-0061, Japan

www.renesas.com

Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.

Contact information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit:

www.renesas.com/contact/.