

RH850/U2Bx

ENCA(Encoder Timer A)

Summary

This application note describes how RH850/U2B6 uses the ENCA input signal to achieve counter clearing and capture. The operation examples shown in this application note have been confirmed to work, but please be sure to check the operating environment before using the product.

Operation confirmation device

RH850/U2B6-FCC (R7F702Z22EDBB)

Table of contents

1.	Introduction.....	2
1.1	Functions.....	2
2.	Capture operation performed when clearing by ENCA _n EC, ENCA _n E0, ENCA _n E1.....	2
2.1	Operation overview.....	2
2.2	Operation flowchart	3
2.3	Software description.....	4
3.	ENCA input signal selection of PIC.....	6
3.1	Operation overview.....	6
3.2	Operation flowchart	7
3.3	Software description.....	7

1. Introduction

In this application note, the capture operation performed at the time of clearing by ENCA_nEC, ENCA_nE0, ENCA_nE1 in ENCA in RH850/U2B6-FCC and the input selection of ENCA by PIC are described.

1.1 Functions

The hardware functions of RH850/U2B6 used in this application note are shown below.

- ENCA (Encoder timer)
- PIC (Peripheral Interconnect)

2. Capture operation performed when clearing by ENCA_nEC, ENCA_nE0, ENCA_nE1

This chapter shows an example of a capture operation that clears the ENCA0 counter with the three input signals ENCA0EC, ENCA0E0, and ENCA0E1. The input to ENCA0 feeds the signal from encoder signal group 0 pin via the PIC1.

2.1 Operation overview

Clear the timer and perform the capture operation of ENCA0.

When an external input signal is input to ENCA0 by PIC1, ENCA0 counts up the counter as the ENCA0E0 and ENCA0E1 inputs change. If the inputs are ENCA0E0 = Low, ENCA0E1 = Low, ENCA0EC = High, ENCA clears the counter and ENCA0CCR1 captures the value of the counter. At this time, the capture interrupt INTENCA0I1 and the clear interrupt INTENCA0IEC are generated. The value of the counter is read by the generated capture interrupt.




Figure 2-1 ENCA0 operation overview

2.2 Operation flowchart

Figure 2-2 shows the operation flowchart of this operation example.




Figure 2-2 ENCA0, PIC1 operation flowchart

2.3 Software description

Table 2-1 to 2-4 show a setting example of each register used in this operation example.

Table 2-1 Register setting example (ENCA0)

Register name	Set value	Function
ENCA0CTL	0x0283	Use ENCA0CCR1 as the capture register Use encoder clear signal as capture trigger Detection of both ends of ENCA0E0 and ENCA0E1
ENCA0IOC1	0xC0	Clear the counter when the following input status is detected ● ENCA0EC = High ● ENCA0E1 = Low ● ENCA0E0 = Low
ENCA0TS	0x01	ENCA0 timer start

Table 2-2 Register setting example (PIC1)

Register name	Set value	Function
PIC1SSER02	0x1000	ENCA0 simulation start trigger enabled
PIC1REG30	0x00000000	Use ENCA0E0 pin input for ENCAT0E0
		Use ENCA0E1 pin input for ENCAT0E1
		Use ENCA0EC pin input for ENCAT0EC

Table 2-3 Register setting example (Interrupt)

Register name	Set value	Function
EIC311	0x0041	INTENCA0I1 (Capture) Table reference method / Priority level 1

Table 2-4 Register setting example (Port)

Register name	Set value	Function
PFCEAE2	0x0007	P2_0, P2_1, P2_2: ALT_IN13 (Alternative input mode 13)
PFCAE2	0x0007	
PFCE2	0x0000	
PFC2	0x0000	
PM2	0x0007	
PMC2	0x0007	
PIPC2	0xFFFF8	P2_0, P2_1, P2_2 : Software I / O control

Tables 2-5 to 2-6 show a list of functions and variables used in this operation example.

Table 2-5 Function list

Function name	Overview
main0	Call each function, Main processing
port_init	Port initialization
enca0_init	ENCA0 initialization
pic1_init	PIC1 initialization
int_cpu0_init	Interrupt function initialization
int_enca0_capture	ENCA0 capture interrupt

Table 2-6 Variable list

Variable name	Overview
g_u2t_counter_capture	Save the captured value

3. ENCA input signal selection of PIC

This chapter shows an example of selecting the input signal of ENCA by PIC.

The ENCA input selection of the PIC1 connects ENCA1 to the encoder signal group 0 pin.

3.1 Operation overview

Set ENCA1 to clear and capture counters by ENCA0EC, ENCA0E0, and ENCA0E1. As the input signal to the set ENCA1, the signal from the encoder signal group 0 pin is selected by PIC1 and supplied.




Figure 3-1 PIC1 operation overview

3.2 Operation flowchart

Figure 3-2 shows the operation flowchart of this operation example.




Figure 3-2 ENCA1, PIC1 operation flowchart

3.3 Software description

Table 3-1 to 3-4 show a setting example of each register used in this operation example.

Table 3-1 Register setting example (ENCA1)

Register name	Set value	Function
ENCA1CTL	0x0283	Use ENCA1CCR1 as the capture register
		Use encoder clear signal as capture trigger
		Detection of both ends of ENCA1E0 and ENCA1E1
ENCA1IOC1	0xC0	Clear the counter when the following input status is detected ● ENCA1EC = High ● ENCA1E1 = Low ● ENCA1E0 = Low
ENCA1TS	0x01	ENCA1 timer start

Table 3-2 Register setting example (PIC1)

Register name	Set value	Function
PIC1SSER02	0x2000	ENCA1 simulation start trigger enabled
PIC1REG30	0x00000940	Use ENCA0E0 pin input for ENCAT1E0
		Use ENCA0E1 pin input for ENCAT1E1
		Use ENCA0EC pin input for ENCAT1EC

Table 3-3 Register setting example (Interrupt)

Register name	Set value	Function
EIC423	0x0041	INTENCA1I1 (Capture) Table reference method / Priority level 1

Table 3-4 Register setting example (Port)

Register name	Set value	Function
PFCEAE2	0x0007	P2_0, P2_1, P2_2: ALT_IN13 (Alternative input mode 13)
PFC AE2	0x0007	
PFCE2	0x0000	
PFC2	0x0000	
PM2	0x0007	
PMC2	0x0007	
PIPC2	0xFFFF8	P2_0, P2_1, P2_2 : Software I / O control

Table 3-5 to 3-6 show a list of functions and variables used in this operation example.

Table 3-5 Function list

Function name	Overview
main0	Call each function, Main processing
port_init	Port initialization
enca1_init	ENCA1 initialization
pic1_init	PIC1 initialization
int_cpu0_init	Interrupt function initialization
int_enca1_capture	ENCA1 capture interrupt

Table 3-6 Variable list

Variable name	Overview
g_u2t_counter_capture	Save the captured value

Revised record

Rev.	Date of issue	Revised contents	
		page	point
1.00	2022.06.30	-	First edition issued

General Precautions in the Handling of Microprocessing Unit and Microcontroller Unit Products

The following usage notes are applicable to all Microprocessing unit and Microcontroller unit products from Renesas. For detailed usage notes on the products covered by this document, refer to the relevant sections of the document as well as any technical updates that have been issued for the products.

1. Precaution against Electrostatic Discharge (ESD)

A strong electrical field, when exposed to a CMOS device, can cause destruction of the gate oxide and ultimately degrade the device operation. Steps must be taken to stop the generation of static electricity as much as possible, and quickly dissipate it when it occurs. Environmental control must be adequate. When it is dry, a humidifier should be used. This is recommended to avoid using insulators that can easily build up static electricity. Semiconductor devices must be stored and transported in an anti-static container, static shielding bag or conductive material. All test and measurement tools including work benches and floors must be grounded. The operator must also be grounded using a wrist strap. Semiconductor devices must not be touched with bare hands. Similar precautions must be taken for printed circuit boards with mounted semiconductor devices.

2. Processing at power-on

The state of the product is undefined at the time when power is supplied. The states of internal circuits in the LSI are indeterminate and the states of register settings and pins are undefined at the time when power is supplied. In a finished product where the reset signal is applied to the external reset pin, the states of pins are not guaranteed from the time when power is supplied until the reset process is completed. In a similar way, the states of pins in a product that is reset by an on-chip power-on reset function are not guaranteed from the time when power is supplied until the power reaches the level at which resetting is specified.

3. Input of signal during power-off state

Do not input signals or an I/O pull-up power supply while the device is powered off. The current injection that results from input of such a signal or I/O pull-up power supply may cause malfunction and the abnormal current that passes in the device at this time may cause degradation of internal elements. Follow the guideline for input signal during power-off state as described in your product documentation.

4. Handling of unused pins

Handle unused pins in accordance with the directions given under handling of unused pins in the manual. The input pins of CMOS products are generally in the high-impedance state. In operation with an unused pin in the open-circuit state, extra electromagnetic noise is induced in the vicinity of the LSI, an associated shoot-through current flows internally, and malfunctions occur due to the false recognition of the pin state as an input signal become possible.

5. Clock signals

After applying a reset, only release the reset line after the operating clock signal becomes stable. When switching the clock signal during program execution, wait until the target clock signal is stabilized. When the clock signal is generated with an external resonator or from an external oscillator during a reset, ensure that the reset line is only released after full stabilization of the clock signal. Additionally, when switching to a clock signal produced with an external resonator or by an external oscillator while program execution is in progress, wait until the target clock signal is stable.

6. Voltage application waveform at input pin

Waveform distortion due to input noise or a reflected wave may cause malfunction. If the input of the CMOS device stays in the area between V_{IL} (Max.) and V_{IH} (Min.) due to noise, for example, the device may malfunction. Take care to prevent chattering noise from entering the device when the input level is fixed, and also in the transition period when the input level passes through the area between V_{IL} (Max.) and V_{IH} (Min.).

7. Prohibition of access to reserved addresses

Access to reserved addresses is prohibited. The reserved addresses are provided for possible future expansion of functions. Do not access these addresses as the correct operation of the LSI is not guaranteed.

8. Differences between products

Before changing from one product to another, for example to a product with a different part number, confirm that the change will not lead to problems. The characteristics of a microprocessing unit or microcontroller unit products in the same group but having a different part number might differ in terms of internal memory capacity, layout pattern, and other factors, which can affect the ranges of electrical characteristics, such as characteristic values, operating margins, immunity to noise, and amount of radiated noise. When changing to a product with a different part number, implement a system-evaluation test for the given product.

Notice

1. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation or any other use of the circuits, software, and information in the design of your product or system. Renesas Electronics disclaims any and all liability for any losses and damages incurred by you or third parties arising from the use of these circuits, software, or information.
2. Renesas Electronics hereby expressly disclaims any warranties against and liability for infringement or any other claims involving patents, copyrights, or other intellectual property rights of third parties, by or arising from the use of Renesas Electronics products or technical information described in this document, including but not limited to, the product data, drawings, charts, programs, algorithms, and application examples.
3. No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights of Renesas Electronics or others.
4. You shall be responsible for determining what licenses are required from any third parties, and obtaining such licenses for the lawful import, export, manufacture, sales, utilization, distribution or other disposal of any products incorporating Renesas Electronics products, if required.
5. You shall not alter, modify, copy, or reverse engineer any Renesas Electronics product, whether in whole or in part. Renesas Electronics disclaims any and all liability for any losses or damages incurred by you or third parties arising from such alteration, modification, copying or reverse engineering.
6. Renesas Electronics products are classified according to the following two quality grades: "Standard" and "High Quality". The intended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below.

"Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; industrial robots; etc.

"High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control (traffic lights); large-scale communication equipment; key financial terminal systems; safety control equipment; etc.

Unless expressly designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not intended or authorized for use in products or systems that may pose a direct threat to human life or bodily injury (artificial life support devices or systems; surgical implantations; etc.), or may cause serious property damage (space system; undersea repeaters; nuclear power control systems; aircraft control systems; key plant systems; military equipment; etc.). Renesas Electronics disclaims any and all liability for any damages or losses incurred by you or any third parties arising from the use of any Renesas Electronics product that is inconsistent with any Renesas Electronics data sheet, user's manual or other Renesas Electronics document.

7. No semiconductor product is absolutely secure. Notwithstanding any security measures or features that may be implemented in Renesas Electronics hardware or software products, Renesas Electronics shall have absolutely no liability arising out of any vulnerability or security breach, including but not limited to any unauthorized access to or use of a Renesas Electronics product or a system that uses a Renesas Electronics product. RENESAS ELECTRONICS DOES NOT WARRANT OR GUARANTEE THAT RENESAS ELECTRONICS PRODUCTS, OR ANY SYSTEMS CREATED USING RENESAS ELECTRONICS PRODUCTS WILL BE INVULNERABLE OR FREE FROM CORRUPTION, ATTACK, VIRUSES, INTERFERENCE, HACKING, DATA LOSS OR THEFT, OR OTHER SECURITY INTRUSION ("Vulnerability Issues"). RENESAS ELECTRONICS DISCLAIMS ANY AND ALL RESPONSIBILITY OR LIABILITY ARISING FROM OR RELATED TO ANY VULNERABILITY ISSUES. FURTHERMORE, TO THE EXTENT PERMITTED BY APPLICABLE LAW, RENESAS ELECTRONICS DISCLAIMS ANY AND ALL WARRANTIES, EXPRESS OR IMPLIED, WITH RESPECT TO THIS DOCUMENT AND ANY RELATED OR ACCOMPANYING SOFTWARE OR HARDWARE, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY, OR FITNESS FOR A PARTICULAR PURPOSE.
8. When using Renesas Electronics products, refer to the latest product information (data sheets, user's manuals, application notes, "General Notes for Handling and Using Semiconductor Devices" in the reliability handbook, etc.), and ensure that usage conditions are within the ranges specified by Renesas Electronics with respect to maximum ratings, operating power supply voltage range, heat dissipation characteristics, installation, etc. Renesas Electronics disclaims any and all liability for any malfunctions, failure or accident arising out of the use of Renesas Electronics products outside of such specified ranges.
9. Although Renesas Electronics endeavors to improve the quality and reliability of Renesas Electronics products, semiconductor products have specific characteristics, such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Unless designated as a high reliability product or a product for harsh environments in a Renesas Electronics data sheet or other Renesas Electronics document, Renesas Electronics products are not subject to radiation resistance design. You are responsible for implementing safety measures to guard against the possibility of bodily injury, injury or damage caused by fire, and/or danger to the public in the event of a failure or malfunction of Renesas Electronics products, such as safety design for hardware and software, including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult and impractical, you are responsible for evaluating the safety of the final products or systems manufactured by you.
10. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. You are responsible for carefully and sufficiently investigating applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive, and using Renesas Electronics products in compliance with all these applicable laws and regulations. Renesas Electronics disclaims any and all liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
11. Renesas Electronics products and technologies shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations. You shall comply with any applicable export control laws and regulations promulgated and administered by the governments of any countries asserting jurisdiction over the parties or transactions.
12. It is the responsibility of the buyer or distributor of Renesas Electronics products, or any other party who distributes, disposes of, or otherwise sells or transfers the product to a third party, to notify such third party in advance of the contents and conditions set forth in this document.
13. This document shall not be reprinted, reproduced or duplicated in any form, in whole or in part, without prior written consent of Renesas Electronics.
14. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products.

(Note1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its directly or indirectly controlled subsidiaries.

(Note2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.

(Rev.5.0-1 October 2020)

Corporate Headquarters

TOYOSU FORESIA, 3-2-24 Toyosu,
Koto-ku, Tokyo 135-0061, Japan

www.renesas.com

Trademarks

Renesas and the Renesas logo are trademarks of Renesas Electronics Corporation. All trademarks and registered trademarks are the property of their respective owners.

Contact information

For further information on a product, technology, the most up-to-date version of a document, or your nearest sales office, please visit:

www.renesas.com/contact/