Old Company Name in Catalogs and Other Documents

On April 1st, 2010, NEC Electronics Corporation merged with Renesas Technology Corporation, and Renesas Electronics Corporation took over all the business of both companies. Therefore, although the old company name remains in this document, it is a valid Renesas Electronics document. We appreciate your understanding.

Renesas Electronics website: http://www.renesas.com

April 1st, 2010 Renesas Electronics Corporation

Issued by: Renesas Electronics Corporation (http://www.renesas.com)

Send any inquiries to http://www.renesas.com/inquiry.



Notice

- 1. All information included in this document is current as of the date this document is issued. Such information, however, is subject to change without any prior notice. Before purchasing or using any Renesas Electronics products listed herein, please confirm the latest product information with a Renesas Electronics sales office. Also, please pay regular and careful attention to additional and different information to be disclosed by Renesas Electronics such as that disclosed through our website.
- Renesas Electronics does not assume any liability for infringement of patents, copyrights, or other intellectual property rights
 of third parties by or arising from the use of Renesas Electronics products or technical information described in this document.
 No license, express, implied or otherwise, is granted hereby under any patents, copyrights or other intellectual property rights
 of Renesas Electronics or others.
- 3. You should not alter, modify, copy, or otherwise misappropriate any Renesas Electronics product, whether in whole or in part.
- 4. Descriptions of circuits, software and other related information in this document are provided only to illustrate the operation of semiconductor products and application examples. You are fully responsible for the incorporation of these circuits, software, and information in the design of your equipment. Renesas Electronics assumes no responsibility for any losses incurred by you or third parties arising from the use of these circuits, software, or information.
- 5. When exporting the products or technology described in this document, you should comply with the applicable export control laws and regulations and follow the procedures required by such laws and regulations. You should not use Renesas Electronics products or the technology described in this document for any purpose relating to military applications or use by the military, including but not limited to the development of weapons of mass destruction. Renesas Electronics products and technology may not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable domestic or foreign laws or regulations.
- 6. Renesas Electronics has used reasonable care in preparing the information included in this document, but Renesas Electronics does not warrant that such information is error free. Renesas Electronics assumes no liability whatsoever for any damages incurred by you resulting from errors in or omissions from the information included herein.
- 7. Renesas Electronics products are classified according to the following three quality grades: "Standard", "High Quality", and "Specific". The recommended applications for each Renesas Electronics product depends on the product's quality grade, as indicated below. You must check the quality grade of each Renesas Electronics product before using it in a particular application. You may not use any Renesas Electronics product for any application categorized as "Specific" without the prior written consent of Renesas Electronics. Further, you may not use any Renesas Electronics product for any application for which it is not intended without the prior written consent of Renesas Electronics. Renesas Electronics shall not be in any way liable for any damages or losses incurred by you or third parties arising from the use of any Renesas Electronics product for an application categorized as "Specific" or for which the product is not intended where you have failed to obtain the prior written consent of Renesas Electronics. The quality grade of each Renesas Electronics product is "Standard" unless otherwise expressly specified in a Renesas Electronics data sheets or data books, etc.

"Standard": Computers; office equipment; communications equipment; test and measurement equipment; audio and visual equipment; home electronic appliances; machine tools; personal electronic equipment; and industrial robots.

"High Quality": Transportation equipment (automobiles, trains, ships, etc.); traffic control systems; anti-disaster systems; anti-crime systems; safety equipment; and medical equipment not specifically designed for life support.

"Specific": Aircraft; aerospace equipment; submersible repeaters; nuclear reactor control systems; medical equipment or systems for life support (e.g. artificial life support devices or systems), surgical implantations, or healthcare intervention (e.g. excision, etc.), and any other applications or purposes that pose a direct threat to human life.

- 8. You should use the Renesas Electronics products described in this document within the range specified by Renesas Electronics, especially with respect to the maximum rating, operating supply voltage range, movement power voltage range, heat radiation characteristics, installation and other product characteristics. Renesas Electronics shall have no liability for malfunctions or damages arising out of the use of Renesas Electronics products beyond such specified ranges.
- 9. Although Renesas Electronics endeavors to improve the quality and reliability of its products, semiconductor products have specific characteristics such as the occurrence of failure at a certain rate and malfunctions under certain use conditions. Further, Renesas Electronics products are not subject to radiation resistance design. Please be sure to implement safety measures to guard them against the possibility of physical injury, and injury or damage caused by fire in the event of the failure of a Renesas Electronics product, such as safety design for hardware and software including but not limited to redundancy, fire control and malfunction prevention, appropriate treatment for aging degradation or any other appropriate measures. Because the evaluation of microcomputer software alone is very difficult, please evaluate the safety of the final products or system manufactured by you.
- 10. Please contact a Renesas Electronics sales office for details as to environmental matters such as the environmental compatibility of each Renesas Electronics product. Please use Renesas Electronics products in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive. Renesas Electronics assumes no liability for damages or losses occurring as a result of your noncompliance with applicable laws and regulations.
- 11. This document may not be reproduced or duplicated, in any form, in whole or in part, without prior written consent of Renesas Electronics
- 12. Please contact a Renesas Electronics sales office if you have any questions regarding the information contained in this document or Renesas Electronics products, or if you have any other inquiries.
- (Note 1) "Renesas Electronics" as used in this document means Renesas Electronics Corporation and also includes its majority-owned subsidiaries.
- (Note 2) "Renesas Electronics product(s)" means any product developed or manufactured by or for Renesas Electronics.



BIPOLAR ANALOG INTEGRATED CIRCUITS μ PC7800A SERIES

THREE TERMINAL POSITIVE VOLTAGE REGULATORS

DESCRIPTION

 μ PC7800A series are monolithic three terminal positive regulators which employ internally current limiting, thermal shut down, output transistor safe operating area protection make them essentially indestructible.

They are improved for ripple rejection ratio, line regulation, load regulation and quiescent current, as comparison of conventional μ PC7800 series.

FEATURES


- · Wide operation temperature range.
- High ripple rejection ratio.
- · Good regulation (line, load).
- · Low quiescent current.
- Built-in protection circuits.
 (over current protection, SOA protection and thermal shut down)

ORDER INFORMATION


TYPE NUMBER	OUTPUT VOLTAGE	PACKAGE	QUALITY GRADE
μPC7805AHF	5 V		
μPC7808AHF	8 V		
μPC7893AHF	9.3 V		·
μPC7812AHF	12 V	MP-45G(ISOLATED TO-220)	Standard
μPC7815AHF	15 V		
μPC7818AHF	18 V		
μPC7824AHF	24 V		

Please refer to "Quality grade on NEC Semiconductor Devices" (Document number IEI-1209) published by NEC Corporation to know the specification of quality grade on the devices and its recommended applications.

EQUIVALENT CIRCUIT



CONNECTION DIAGRAM






ABSOLUTE MAXIMUM RATINGS (Ta = 25 °C)

CHARACTERISTIC	SYMBOL	RATING	UNIT
Input Voltage	Vin	35/40 (Note1)	V
Internal Power Dissipation	PT	15 ^(Note2)	W
Operating Ambient Temperature Range	Topt	- 30 to + 85	°C
Operating Junction Temperature Range	Topt(j)	- 30 to + 150	°C
Storage Temperature Range	T _{stg}	- 55 to + 150	°C
Thermal Resistance (junction to case)	Rth(j-c)	5	°C/W
Thermal Resistance (junction to ambient)	Rth(j-a)	65	°C/W

(Note1) μ PC7805A, 08A, 93A, 12A, 15A, 18A : 35 V, μ PC7824A : 40 V (Note2) Internally limited

TYPICAL CONNECTION



C1: Required if regulator is located an appreciable distance from power supply filter.

C2: More than 0.1 μ F D1: Needed for ViN < Vo D2: Needed for Vo < GND

RECOMMENDED OPERATING CONDITIONS

CHARACTERISTIC	SYMBOL		MIN.	TYP.	MAX.	UNIT
		μ PC7805 AHF	7	10	25	
		μPC7808AHF	10.5	14	25	
		μPC7893AHF	12	15	24.5	
Input Voltage	Vin	μPC7812AHF	14.5	19	30	V
		μPC7815AHF	17.5	23	30	
		μPC7818AHF	21	27	33	
		μPC7824AHF	27	33	38	
Output Current	lo	All	0.005	0.5	1	Α
Operating Junction Temperature Range	Topt(j)	All	- 30		+ 125	°C



ELECTRICAL CHARACTERISTICS µPC7805A

(Vin = 10 V, lo = 500 mA, $0 \,^{\circ}$ C \leq T_j \leq + 125 $^{\circ}$ C)

CHARACTERISTIC	SYMBOL	TEST CONDITIONS	MIN.	TYP.	MAX.	UNIT	
,		T _j = 25 °C	4.8	5.0	5.2	- v	
Output Voltage	Vo	7 V ≤ Vin ≤ 20 V, 5 mA ≤ lo ≤ 1 A, Pt ≤ 15 W	4.75		5.25		
		- 30 °C ≤ T _j ≤ + 125 °C	4.75		5.25	1	
Line Regulation	REGIN	$T_j = 25$ °C, 7 V \leq VIN \leq 25 V		7	30	mV	
Line Regulation	REGIN	T _j = 25 °C, 8 V ≦ V _{IN} ≦ 12 V		2	15	1110	
Load Regulation	REGL	$T_j = 25 ^{\circ}\text{C}, 5 \text{mA} \leq I_0 \leq 1.5 \text{A}$		4	30	>/	
Load Regulation	NEGL	T _j = 25 °C, 250 mA ≦ Io ≦ 750 mA		2	10	10 mV	
Quiescent Current	IBIAS	T _j = 25 °C		2.8	4.3	mA	
Quiescent Current	Albias	7 V ≦ V _{IN} ≦ 25 V			1.0		
Change	ZIBIAS	5 mA ≤ lo ≤ 1.0 A			0.5	mA	
Output Noize Voltage	V _n	$T_j = 25 ^{\circ}\text{C}$, 10 Hz $\leq f \leq$ 100 kHz		40	200	μVr.m.s.	
Ripple Rejection	R•R	Tj = 25 °C, f = 120 Hz, 8 V ≦ VIN ≦ 18 V	70	76		dB	
Dropout Voltage	V DIF	T _j = 25 °C, lo = 1.0 A		1.8		V	
Short Circuit Current	lOshort	T _j = 25 °C, V _{IN} = 25 V		1.6		Α	
Peak Output Current	lOpeak	T _j = 25 °C, V _I N ≈ 10 V	1.7	2.2	2.8	Α	
Temperature Coefficient of Output Voltage	ΔVο/ΔΤ	lo = 5 mA, 0 °C ≦ T _j ≦ + 125 °C		- 0.4		mV/°C	

ELECTRICAL CHARACTERISTICS μPC7808A

(Vin = 14 V, lo = 500 mA, $0 \,^{\circ}$ C $\leq T_{j} \leq + 125 \,^{\circ}$ C)

CHARACTERISTIC	SYMBOL	TEST CONDITIONS	MIN.	TYP.	MAX.	UNIT	
		Tj = 25 °C	7.7	8.0	8.3	V	
Output Voltage	Vo	$10.5 \text{ V} \leq \text{Vin} \leq 23 \text{ V}, 5 \text{ mA} \leq \text{Io} \leq 1 \text{ A}, \text{Pt} \leq 15 \text{ W}$	7.6		8.4		
		- 30 °C ≦ T _i ≦ + 125 °C	7.6		8.4		
Line Deculation	DEC	$T_i = 25 ^{\circ}\text{C}, \ 10.5 ^{\vee}\text{V} \leq \text{Vin} \leq 25 ^{\vee}\text{V}$		8	35		
Line Regulation	REGIN	T _i = 25 °C, 11 V ≦ V _{IN} ≦ 17 V		3	25	mV	
Lond Domilation	DEO	$T_j = 25$ °C, 5 mA $\leq 10 \leq 1.5$ A		12	90		
Load Regulation	REGL	T _j = 25 °C, 250 mA ≦ lo ≦ 750 mA		4	20	mV	
Quiescent Current	BIAS	T _j = 25 °C		3	4.4	mA	
Quiescent Current	Alman	10.5 V ≦ Vin ≦ 25 V			1.0	A	
Change	∆IBIAS	5 mA ≦ to ≦ 1.0 A			0.5	mA	
Output Noize Voltage	Vn	$T_i = 25$ °C, 10 Hz $\leq f \leq$ 100 kHz		50	250	μVr.m.s.	
Ripple Rejection	R•R	$T_i = 25$ °C, $f = 120$ Hz, 11.5 V \leq ViN \leq 21.5 V	66	72		dB	
Dropout Voltage	VDIF	T _j = 25 °C, Io = 1.0 A		1.8		V	
Short Circuit Current	Oshort	T _j = 25 °C, V _{IN} = 25 V		1.6		Α	
Peak Output Current	lOpeak	T _j = 25 °C, V _{IN} = 14 V	1.7	2.2	2.8	Α	
Temperature Coefficient of Output Voltage	ΔVο/ΔΤ	lo = 5 mA, 0 °C ≦ T _j ≦ + 125 °C		- 0.6		mV/°C	



ELECTRICAL CHARACTERISTICS μ PC7812A

(Vin = 19 V, Io = 500 mA, $0 \,^{\circ}$ C \leq Tj \leq + 125 $^{\circ}$ C)

CHARACTERISTIC	SYMBOL	TEST CONDITIONS	MIN.	TYP.	MAX.	UNIT
		T _j = 25 °C	25 °C 11.5 12		12.5	
Output Voltage	Vo	$14.5 \text{ V} \leq \text{V}_{\text{IN}} \leq 27 \text{ V}, 5 \text{ mA} \leq \text{Io} \leq 1 \text{ A, Pt} \leq 15 \text{ W}$	11.4		12.6 V	
		30 °C ≦ T _j ≦ + 125 °C	11.4		12.6	
li Dl.ai	DEC	$T_j = 25$ °C, 14.5 V \leq VIN \leq 30 V		10	45	\/
Line Regulation	REGIN	T _j = 25 °C, 16 V ≦ V _{IN} ≦ 22 V		4	30	mV
1 15 12	550	T _j = 25 °C, 5 mA ≦ lo ≦ 1.5 A		17	130	.,
Load Regulation	REG∟	$T_j = 25 ^{\circ}\text{C}, 250 \text{mA} \leq I_0 \leq 750 \text{mA}$		6 30	mV	
Quiescent Current	IBIAS	T _j = 25 °C		3.1	4.6	mA
Quiescent Current		14.5 V ≦ VIN ≦ 30 V			1.0	mA
Change	∆IBIAS	5 mA ≤ lo ≤ 1.0 A			0.5	""
Output Noize Voltage	Vn	T _j = 25 °C, 10 Hz ≦ f ≦ 100 kHz		70	300	μVr.m.s.
Ripple Rejection	R•R	T _j = 25 °C, f = 120 Hz,15 V ≦ V _{IN} ≦ 25 V	62	68		dB
Dropout Voltage	VDIF	T _j = 25 °C, lo = 1.0 A		1.8		V
Short Circuit Current	lOshort	T _j = 25 °C, V _I N = 30 V		1.3		Α
Peak Output Current	Opeak	T _j = 25 °C, V _{IN} = 19 V	1.7	2.2	2.8	Α
Temperature Coefficient of Output Voltage	ΔVο/ΔΤ	Io = 5 mA, 0 °C ≦ T _j ≦ + 125 °C		- 0.8		mV/°C

ELECTRICAL CHARACTERISTICS µPC7815A

 $(Vin = 23 V, Io = 500 mA, 0 °C \le T_j \le + 125 °C)$

CHARACTERISTIC	SYMBOL	TEST CONDITIONS	MIN.	TYP.	MAX.	UNIT	
CHARACTERISTIC	STIVIBUL			15.0	15.6	OIVIT	
		T _j = 25 °C	14.4	15.0		1 , 1	
Output Voltage	Vo	$17.5 \text{ V} \leq \text{Vin} \leq 30 \text{ V}, 5 \text{ mA} \leq \text{Io} \leq 1 \text{ A}, \text{ Pr} \leq 15 \text{ W}$	14.25		15.75	V	
		– 30 °C ≦ Tj ≦ + 125 °C	14.25		15.75		
1. 6	DEC	$T_j = 25 ^{\circ}\text{C}, 17.5 ^{\circ}\text{V} \leq \text{Vin} \leq 30 ^{\circ}\text{V}$		10	45	\/	
Line Regulation	REGIN	$T_j = 25$ °C, 20 V \leq VIN \leq 26 V		5	35	mV	
		T _j = 25 °C, 5 mA ≦ lo ≦ 1.5 A		25	190	\/	
Load Regulation	REG∟	T _i = 25 °C, 250 mA ≦ lo ≦ 750 mA		8	40	mV	
Quiescent Current	IBIAS	T _j = 25 °C		3.3	4.8	mA	
Quiescent Current		17.5 V ≦ VIN ≦ 30 V			1.0		
Change	∆IBIAS	5 mA ≦ lo ≦ 1.0 A			0.5	mA	
Output Noize Voltage	Vn	T _j = 25 °C, 10 Hz ≦ f ≦ 100 kHz		85	400	μVr.m.s.	
Ripple Rejection	R•R	$T_j = 25 ^{\circ}\text{C}$, $f = 120 ^{\circ}\text{Hz}$, $18.5 ^{\circ}\text{V} \leq \text{Vin} \leq 28.5 ^{\circ}\text{V}$	60	66		dB	
Dropout Voltage	VDIF	T _j = 25 °C, lo = 1.0 A		1.8		V	
Short Circuit Current	lOshort	T _j = 25 °C, V _{IN} = 30 V		1.3		Α	
Peak Output Current	lOpeak	T _j = 25 °C, V _I N = 23 V	1.7	2.2	2.8	Α	
Temperature Coefficient of Output Voltage	ΔVο/ΔΤ	Io = 5 mA, 0 °C ≦ T _j ≦ + 125 °C		- 1.1		mV/°C	



ELECTRICAL CHARACTERISTICS μ PC7818A

(VIN = 27 V, lo = 500 mA, $0 \,^{\circ}$ C \leq T_j \leq + 125 $^{\circ}$ C)

CHARACTERISTIC	SYMBOL	TEST CONDITIONS	MIN.	TYP.	MAX.	UNIT
		T _j = 25 °C	17.3	18.0	18.7	
Output Voltage	Vo	$21 \text{ V} \leq \text{Vin} \leq 33 \text{ V}, 5 \text{ mA} \leq \text{Io} \leq 1 \text{ A}, \text{Pt} \leq 15 \text{ W}$	17.1		18.9	V
		-30 °C ≤ T _i ≤ + 125 °C	17.1		18.9	
Line Begulation	DEC	$T_j = 25$ °C, $21 \text{ V} \leq V_{IN} \leq 33 \text{ V}$		12	60	m۷
Line Regulation	REGIN	$T_j = 25$ °C, 24 V \leq VIN \leq 30 V		6	45	
Lond Regulation	DEC	$T_j = 25$ °C, 5 mA $\leq I_0 \leq 1.5$ A		32	110	mV
Load Regulation	REGL	$T_j = 25$ °C, 250 mA $\leq I_0 \leq 750$ mA		10	40	
Quiescent Current	IBIAS	T _j = 25 °C		3.4	5.0	mA
Quiescent Current	∆IBIAS	21 V ≦ Vin ≦ 33 V			1.0	mA
Change	ZIBIAS	5 mA ≦ lo ≦ 1.0 A			0.5	
Output Noize Voltage	Vn	Tj = 25 °C, 10 Hz ≦ f ≦ 100 kHz		95	450	μVr.m.s.
Ripple Rejection	R•R	$T_{j} = 25 ^{\circ}\text{C}, f = 120 \text{Hz}, 22 \text{V} \le \text{Vin} \le 32 \text{V}$	59	65		dB
Dropout Voltage	VDIF	T _j = 25 °C, lo = 1.0 A		1.8		V
Short Circuit Current	Oshort	Tj = 25 °C, VIN = 33 V		1.2		Α
Peak Output Current	lOpeak	Tj = 25 °C, VIN = 27 V	1.7	2.2	2.8	Α
Temperature Coefficient of Output Voltage	ΔVο/ΔΤ	Io = 5 mA, 0 °C ≦ T _j ≦ + 125 °C		- 1.3		mV/°C

ELECTRICAL CHARACTERISTICS µPC7824A

 $(V_{IN} = 33 \text{ V, Io} = 500 \text{ mA, } 0 ^{\circ}\text{C} \le T_{j} \le + 125 ^{\circ}\text{C})$


CHARACTERISTIC	SYMBOL	TEST CONDITIONS	MIN.	TYP.	MAX.	UNIT	
		T _j = 25 °C	23.0	24.0	25.0		
Output Voltage	Vo	$27 \text{ V} \leq \text{Vin} \leq 38 \text{ V}, 5 \text{ mA} \leq \text{lo} \leq 1 \text{ A}, \text{Pt} \leq 15 \text{ W}$	22.8		25.2	\ \ \	
		- 30 °C ≦ T _j ≦ + 125 °C	22.8		25.2]	
Line Regulation	REGIN	T _j = 25 °C, 27 V ≦ V _{IN} ≦ 38 V		15	80	>/	
Line Regulation	NEGIN	$T_j = 25$ °C, 30 V \leq VIN \leq 36 V		8	50	mV	
Load Regulation	DEC.	$T_j = 25$ °C, 5 mA $\leq I_0 \leq 1.5$ A		44	150		
Load Regulation	REGL	T _j = 25 °C, 250 mA ≦ Io ≦ 750 mA		14	50	mV	
Quiescent Current	IBIAS	T _j = 25 °C		3.6	5.3	mA	
Quiescent Current	41	27 V ≦ V _I N ≦ 38 V			1.0		
Change	∆IBIAS	5 mA ≦ lo ≦ 1.0 A			0.5	mA	
Output Noize Voltage	Vn	$T_j = 25$ °C, 10 Hz $\leq f \leq$ 100 kHz		120	500	μVr.m.s.	
Ripple Rejection	R•R	$T_i = 25 ^{\circ}\text{C}$, $f = 120 \text{Hz}$, $28 \text{V} \le \text{Vin} \le 38 \text{V}$	55	62		dB	
Dropout Voltage	VDIF	T _j = 25 °C, I _o = 1.0 A		2.0		V	
Short Circuit Current	Oshort	T _j = 25 °C, V _{IN} = 38 V		1.0		Α	
Peak Output Current	lOpeak	T _j = 25 °C, V _{IN} = 33 V	1.7	2.2	2.8	Α	
Temperature Coefficient of Output Voltage	ΔVο/ΔΤ	lo = 5 mA, 0 °C ≦ T; ≦ + 125 °C		- 1.7		mV/°C	





ELECTRICAL CHARACTERISTICS μ PC7893A


(Vin = 15 V, Io = 500 mA, $0 \,^{\circ}$ C \leq T_j \leq + 125 $^{\circ}$ C)


TYPICAL CHARACTERISTICS (Ta = 25 °C)
























PACKAGE DIMENSIONS

3PIN PLASTIC SIP (MP-45G)



P3HF-254B-1

NOTE

Each lead centerline is located within 0.25 mm (0.01 inch) of its true position (T.P.) at maximum material condition.

ITEM	MILLIMETERS	INCHES
Α	10.4 MAX.	0.410 MAX.
В	7.0	0.276
С	1.2 MIN.	0.047 MIN.
D	17.0 ^{±0.3}	0.669+0.013
E	$\phi 3.3^{\pm 0.2}$	φ0.130 ^{±0.008}
F	0.75 ^{±0.10}	0.030+0.004
G	0.25	0.010
Н	2.54 (T.P.)	0.100 (T.P.)
ı	5.0 ^{±0.3}	0.197 ^{±0.012}
J	2.66 MAX.	0.105 MAX.
К	4.8 MIN.	0.188 MIN.
L	8.5	0.335
М	8.5	0.335
N	4.5 ^{±0.2}	0.177 ^{±0.008}
Р	2.8 ^{±0.2}	0.110 -0.009
Q	22.4 MAX.	0.882 MAX.
U	2.4 ^{±0.5}	0.094 - 0.021
V	0.65 ^{±0.10}	0.026 - 0.005
Υ	8.9 ^{±0.7}	0.350 ^{±0.028}
Z	1.0 MIN.	0.039 MIN.

RECOMMENDED SOLDERING CONDITIONS

The following conditions (see table below) must be met when soldering this product. Please consult with our sales offices in case other soldering process is used, or in case soldering is done under different conditions.

TYPES OF THROUGH HOLE MOUNT DEVICE

μPC7800AHF Series

Soldering process	Soldering conditions	Symbol
Wave soldering	Solder temperature : 260 °C or below.	
vvave soldering	Flow time: 10 seconds or below.	



[MEMO]



[MEMO]



NEC Corporation does not assume any liability for infringement of patents, copyrights or other intellectual property rights of third parties by or arising from use of a device described herein or any other liability arising from use of such device. No license, either express, implied or otherwise, is granted under any patents, copyrights or other intellectual property rights of NEC Corporation or others.

The devices listed in this document are not suitable for use in aerospace equipment, submarine cables, nuclear reactor control systems and life support systems. If customers intend to use NEC devices for above applications or they intend to use "Standard" quality grade NEC devices for applications not intended by NEC, please contact our sales people in advance.

Application examples recommended by NEC Corporation.

Standard: Computer, Office equipment, Communication equipment, Test and Measurement equipment, Machine tools, Industrial robots, Audio and Visual equipment, Other consumer products, etc.

Special: Automotive and Transportation equipment, Traffic control systems, Antidisaster systems, Anticrime systems, etc.

M4 92.6