JEITA Package Code	RENESAS Code	Previous Code	MASS (TYP.) [g]
P-DIP8-0300-2.54	PRDP0008AH-D	P8C-100-300C	0.48





## NOTES

2. Item "K" to center of leads when formed parallel.



ITEM	MILLIMETERS	
А	10.16 MAX.	
В	1.27 MAX.	
С	2.54 (T.P.)	
D	0.50±0.10	
F	1.4 MIN.	
G	3.2±0.3	
Н	0.51 MIN.	
Ι	4.31 MAX.	
J	5.08 MAX.	
К	7.62 (T.P.)	
L	6.4	
М	$0.25\substack{+0.10 \\ -0.05}$	
N	0.25	
Р	0.9 MIN.	
R	0~15°	

 $\ensuremath{\textcircled{O}}$  2012 Renesas Electronics Corporation. All rights reserved.

<sup>1.</sup> Each lead centerline is located within 0.25 mm of its true position (T.P.) at maximum material condition.